

1.4 INFORMATIONAL SUBMITTALS

- A. Coordination Drawings: Floor plans and sections, drawn to scale, on which the following items are shown and coordinated with each other, using input from installers of the items involved:
 - 1. Scaled cable tray layout and relationships between components and adjacent structural, electrical, and mechanical elements.
 - 2. Vertical and horizontal offsets and transitions.
 - 3. Clearances for access above and to side of cable trays.
 - 4. Vertical elevation of cable trays above the floor or below bottom of ceiling structure.
- B. Seismic Qualification Certificates: For cable trays, accessories, and components, from manufacturer.
 - 1. Basis for Certification: Indicate whether withstand certification is based on actual test of assembled components or on calculation.
 - 2. Dimensioned Outline Drawings of Equipment Unit: Identify center of gravity and locate and describe mounting and anchorage provisions.
 - 3. Detailed description of equipment anchorage devices on which the certification is based and their installation requirements.
- C. Field quality-control reports.

PART 2 - PRODUCTS

2.1 PERFORMANCE REQUIREMENTS

- A. Delegated Design: Engage a qualified professional engineer, as defined in Section 014000 "Quality Requirements," to design cable tray supports and seismic bracing.
- B. Seismic Performance: Cable trays and supports shall withstand the effects of earthquake motions determined according to **ASCE/SEI 7**.
 - 1. The term "withstand" means "cable trays will remain in place without separation of any parts when subjected to the seismic forces specified."
 - 2. Component Importance Factor: **1.5**.
- C. Thermal Movements: Allow for thermal movements from ambient and surface temperature changes in cable tray installed outdoors.
 - 1. Temperature Change: **120 deg F (67 deg C), ambient; 180 deg F (100 deg C), material surfaces.**

2.2 GENERAL REQUIREMENTS FOR CABLE TRAY

- A. Cable Trays and Accessories: Identified as defined in NFPA 70 and marked for intended location, application, and grounding.
 - 1. Source Limitations: Obtain cable trays and components from single manufacturer.

- B. Sizes and Configurations: See the Cable Tray Schedule on Drawings for specific requirements for types, materials, sizes, and configurations.
- C. Structural Performance: See articles on individual cable tray types for specific values for the following parameters:
 - 1. Uniform Load Distribution: Capable of supporting a uniformly distributed load on the indicated support span when supported as a simple span and tested according to NEMA VE 1.
 - 2. Concentrated Load: A load applied at midpoint of span and centerline of tray.
 - 3. Load and Safety Factors: Applicable to both side rails and rung capacities.

2.3 LADDER CABLE TRAY

A. Description:

- 1. Configuration: Two longitudinal side rails with transverse rungs swaged or welded to side rails, complying with NEMA VE 1.
- 2. Width, **18 inches (450 mm)** unless otherwise indicated on Drawings.
- 3. Minimum Usable Load Depth: **4 inches (100 mm)**.
- 4. Straight Section Lengths: **10 feet (3.0 m)** except where shorter lengths are required to facilitate tray assembly.
- 5. Rung Spacing: **6 inches (150 mm)** o.c.
- 6. Radius-Fitting Rung Spacing: 9 inches (225 mm) at center of tray's width.
- 7. Minimum Cable-Bearing Surface for Rungs: 7/8-inch (22-mm) width with radius edges.
- 8. No portion of the rungs shall protrude below the bottom plane of side rails.
- 9. Structural Performance of Each Rung: Capable of supporting a maximum cable load, with a safety factor of 1.5, plus a 200-lb (90-kg) concentrated load, when tested according to NEMA VE 1.
- 10. Fitting Minimum Radius: **12 inches (300 mm)**.
- 11. Class Designation: Comply with NEMA VE 1, **Class 10A**.
- 12. Splicing Assemblies: Bolted type using serrated flange locknuts.
- 13. Splice-Plate Capacity: Splices located within support span shall not diminish rated loading capacity of cable tray.
- 14. Covers: None required.

B. Materials and Finishes:

- 1. Aluminum:
 - a. Materials: Alloy 6063-T6 according to ANSI H35.1/H 35.1M for extruded components, and **Alloy 6061-T6** according to ANSI H35.1/H 35.1M for fabricated parts.
 - b. Hardware for Aluminum Cable Tray Used Outdoors: Stainless steel, Type 316, ASTM F 593 and ASTM F 594.

2.4 CABLE TRAY ACCESSORIES

- A. Fittings: Tees, crosses, risers, elbows, and other fittings as indicated, of same materials and finishes as cable tray.
- B. Barrier Strips: Same materials and finishes as for cable tray.
- C. Cable tray supports and connectors, including bonding jumpers, as recommended by cable tray manufacturer.

2.5 WARNING SIGNS

- A. Lettering: **1-1/2-inch- (40-mm-)** high, black letters on yellow background, with legend **"WARNING! NOT TO BE USED AS WALKWAY, LADDER, OR SUPPORT FOR LADDERS OR PERSONNEL."**
- B. Comply with Section 260553 "Identification for Electrical Systems."

2.6 SOURCE QUALITY CONTROL

- A. Testing: Test and inspect cable trays according to **NEMA VE 1**.

PART 3 - EXECUTION

3.1 CABLE TRAY INSTALLATION

- A. Install cable tray and support systems according to **NEMA VE 2**.
- B. Install cable tray as a complete system, including fasteners, hold-down clips, support systems, barrier strips, adjustable horizontal and vertical splice plates, elbows, reducers, tees, crosses, cable dropouts, adapters, covers, and bonding.
- C. Install cable tray, so that the tray is accessible for cable installation and all splices are accessible for inspection and adjustment.
- D. Remove burrs and sharp edges from cable trays.
- E. Join aluminum cable tray with splice plates; use four square-neck carriage bolts and locknuts.
- F. Fasten cable tray supports to equipment structure **and install seismic restraints**.
- G. Design fasteners and supports to carry cable tray, cables, and a concentrated load of 200 lb (90 kg).
- H. Place supports, so that spans do not exceed maximum spans on schedules, and provide clearances shown on Drawings. Install intermediate supports when cable weight exceeds the load-carrying capacity of tray rungs.

- I. Construct supports from channel members, threaded rods, and other appurtenances furnished by cable tray manufacturer. Arrange supports in trapeze or wall-bracket form as required by application.
- J. Support assembly to prevent twisting from eccentric loading.
- K. Install center-hung supports for single-rail trays designed for 60 versus 40 percent eccentric loading condition, with a safety factor of 3.
- L. Do not install more than one cable tray splice between supports.
- M. Make connections to equipment with flanged fittings fastened to cable trays and to equipment. Support cable trays independent of fittings. Do not carry weight of cable trays on equipment enclosure.
- N. Install expansion connectors where cable trays cross building expansion joints and in cable tray runs that exceed recommended dimensions. Space connectors and set gaps according to applicable standard.
- O. Make changes in direction and elevation using manufacturer's recommended fittings.
- P. Make cable tray connections using manufacturer's recommended fittings.
- Q. Seal penetrations through fire and smoke barriers. Comply with requirements in Section 078413 "Penetration Firestopping."
- R. Install capped metal sleeves for future cables through firestop-sealed cable tray penetrations of fire and smoke barriers.
- S. Install cable trays with enough workspace to permit access for installing cables.
- T. Install barriers to separate cables of different systems, such as power, communications, and data processing, or of different insulation levels, such as 600, 5000, and 15 000 V.
- U. Install permanent covers[**and cover clamps**], if used, after installing cable.
- V. Clamp covers on cable trays installed outdoors with heavy-duty clamps.
- W. Install warning signs in visible locations on or near cable trays after cable tray installation.

3.2 CABLE TRAY GROUNDING

- A. Ground cable trays according to NFPA 70 unless additional grounding is specified. Comply with requirements in Section 260526 "Grounding and Bonding for Electrical Systems."
- B. Cable trays with electrical power conductors shall be bonded together with splice plates listed for grounding purposes or with listed bonding jumpers.
- C. Cable trays with single-conductor power conductors shall be bonded together with a grounding conductor run in the tray along with the power conductors and bonded to the tray at 72-inch (1800-

mm) intervals. The grounding conductor shall be sized according to NFPA 70, Article 250.122, "Size of Equipment Grounding Conductors," and Article 392, "Cable Trays."

- D. When using epoxy- or powder-coat painted cable trays as a grounding conductor, completely remove coating at all splice contact points or ground connector attachment. After completing splice-to-grounding-bolt attachment, repair the coated surfaces with coating materials recommended by cable tray manufacturer.
- E. Bond cable trays to power source for cables contained within with bonding conductors sized according to NFPA 70, Article 250.122, "Size of Equipment Grounding Conductors."

3.3 CABLE INSTALLATION

- A. Install cables only when each cable tray run has been completed and inspected.
- B. Fasten cables on horizontal runs with cable clamps or cable ties. Tighten clamps only enough to secure the cable, without indenting the cable jacket. Install cable ties with a tool that includes an automatic pressure-limiting device.
- C. Fasten cables on vertical runs to cable trays every 18 inches (450 mm).
- D. Fasten and support cables that pass from one cable tray to another or drop from cable trays to equipment enclosures. Fasten cables to the cable tray at the point of exit and support cables independent of the enclosure. The cable length between cable trays or between cable tray and enclosure shall be no more than 72 inches (1800 mm).
- E. Tie mineral-insulated cables down every 36 inches (900 mm) where required to provide a two-hour fire rating and every 72 inches (1800 mm) elsewhere.
- F. In existing construction, remove inactive or dead cables from cable trays.

3.4 CONNECTIONS

- A. Remove paint from all connection points before making connections. Repair paint after the connections are completed.
- B. Connect raceways to cable trays according to requirements in NEMA VE 2 and NEMA FG 1.

3.5 FIELD QUALITY CONTROL

- A. Perform the following tests and inspections **with the assistance of a factory-authorized service representative**:
 - 1. After installing cable trays and after electrical circuitry has been energized, survey for compliance with requirements.
 - 2. Visually inspect cable insulation for damage. Correct sharp corners, protuberances in cable trays, vibrations, and thermal expansion and contraction conditions, which may cause or have caused damage.

3. Verify that the number, size, and voltage of cables in cable trays do not exceed that permitted by NFPA 70. Verify that communications or data-processing circuits are separated from power circuits by barriers or are installed in separate cable trays.
4. Verify that there are no intruding items, such as pipes, hangers, or other equipment, in the cable tray.
5. Remove dust deposits, industrial process materials, trash of any description, and any blockage of tray ventilation.
6. Visually inspect each cable tray joint and each ground connection for mechanical continuity. Check bolted connections between sections for corrosion. Clean and retorqued in suspect areas.
7. Check for improperly sized or installed bonding jumpers.
8. Check for missing, incorrect, or damaged bolts, bolt heads, or nuts. When found, replace with specified hardware.
9. Perform visual and mechanical checks for adequacy of cable tray grounding; verify that all takeoff raceways are bonded to cable trays. Test entire cable tray system for continuity. Maximum allowable resistance is 1 ohm.

B. Prepare test and inspection reports.

3.6 PROTECTION

A. Protect installed cable trays and cables.

1. Install temporary protection for cables in open trays to safeguard exposed cables against falling objects or debris during construction. Temporary protection for cables and cable tray can be constructed of wood or metal materials and shall remain in place until the risk of damage is over.
2. Repair damage to galvanized finishes with zinc-rich paint recommended by cable tray manufacturer.
3. Repair damage to paint finishes with matching touchup coating recommended by cable tray manufacturer.

END OF SECTION 260536

SECTION 260544 - SLEEVES AND SLEEVE SEALS FOR ELECTRICAL RACEWAYS AND CABLING

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:

1. Sleeves for raceway and cable penetration of non-fire-rated construction walls and floors.
2. Sleeve-seal systems.
3. Sleeve-seal fittings.
4. Grout.
5. Silicone sealants.

- B. Related Requirements:

1. Section 078413 "Penetration Firestopping" for penetration firestopping installed in fire-resistance-rated walls, horizontal assemblies, and smoke barriers, with and without penetrating items.

1.3 ACTION SUBMITTALS

- A. Product Data: For each type of product.

PART 2 - PRODUCTS

2.1 SLEEVES

- A. Wall Sleeves:

1. Steel Pipe Sleeves: ASTM A 53/A 53M, Type E, Grade B, Schedule 40, zinc coated, plain ends.
2. Cast-Iron Pipe Sleeves: Cast or fabricated "wall pipe," equivalent to ductile-iron pressure pipe, with plain ends and integral waterstop unless otherwise indicated.

- B. Sleeves for Conduits Penetrating Non-Fire-Rated Gypsum Board Assemblies: Galvanized-steel sheet; 0.0239-inch (0.6-mm) minimum thickness; round tube closed with welded longitudinal joint, with tabs for screw-fastening the sleeve to the board.

- C. PVC-Pipe Sleeves: ASTM D 1785, Schedule 40.
- D. Molded-PVC Sleeves: With nailing flange for attaching to wooden forms.
- E. Molded-PE or -PP Sleeves: Removable, tapered-cup shaped, and smooth outer surface with nailing flange for attaching to wooden forms.
- F. Sleeves for Rectangular Openings:
 - 1. Material: Galvanized sheet steel.
 - 2. Minimum Metal Thickness:
 - a. For sleeve cross-section rectangle perimeter less than 50 inches (1270 mm) and with no side larger than 16 inches (400 mm), thickness shall be 0.052 inch (1.3 mm).
 - b. For sleeve cross-section rectangle perimeter 50 inches (1270 mm) or more and one or more sides larger than 16 inches (400 mm), thickness shall be 0.138 inch (3.5 mm).

2.2 SLEEVE-SEAL SYSTEMS

- A. Description: Modular sealing device, designed for field assembly, to fill annular space between sleeve and raceway or cable.
 - 1. Sealing Elements: **EPDM** rubber interlocking links shaped to fit surface of pipe. Include type and number required for pipe material and size of pipe.
 - 2. Pressure Plates: **Carbon steel**.
 - 3. Connecting Bolts and Nuts: **Carbon steel, with corrosion-resistant coating**, of length required to secure pressure plates to sealing elements.

2.3 SLEEVE-SEAL FITTINGS

- A. Description: Manufactured plastic, sleeve-type, waterstop assembly made for embedding in concrete slab or wall. Unit shall have plastic or rubber waterstop collar with center opening to match piping OD.

2.4 GROUT

- A. Description: Nonshrink; recommended for interior and exterior sealing openings in non-fire-rated walls or floors.
- B. Standard: ASTM C 1107/C 1107M, Grade B, post-hardening and volume-adjusting, dry, hydraulic-cement grout.
- C. Design Mix: 5000-psi (34.5-MPa), 28-day compressive strength.
- D. Packaging: Premixed and factory packaged.

2.5 SILICONE SEALANTS

- A. Silicone Sealants: Single-component, silicone-based, neutral-curing elastomeric sealants of grade indicated below.
 - 1. Grade: Pourable (self-leveling) formulation for openings in floors and other horizontal surfaces that are not fire rated.
- B. Silicone Foams: Multicomponent, silicone-based liquid elastomers that, when mixed, expand and cure in place to produce a flexible, nonshrinking foam.

PART 3 - EXECUTION

3.1 SLEEVE INSTALLATION FOR NON-FIRE-RATED ELECTRICAL PENETRATIONS

- A. Comply with NECA 1.
- B. Comply with NEMA VE 2 for cable tray and cable penetrations.
- C. Sleeves for Conduits Penetrating Above-Grade Non-Fire-Rated Concrete and Masonry-Unit Floors and Walls:
 - 1. Interior Penetrations of Non-Fire-Rated Walls and Floors:
 - a. Seal annular space between sleeve and raceway or cable, using joint sealant appropriate for size, depth, and location of joint. Comply with requirements in Section 079200 "Joint Sealants."
 - b. Seal space outside of sleeves with mortar or grout. Pack sealing material solidly between sleeve and wall so no voids remain. Tool exposed surfaces smooth; protect material while curing.
 - 2. Use pipe sleeves unless penetration arrangement requires rectangular sleeved opening.
 - 3. Size pipe sleeves to provide **1/4-inch (6.4-mm)** annular clear space between sleeve and raceway or cable unless sleeve seal is to be installed.
 - 4. Install sleeves for wall penetrations unless core-drilled holes or formed openings are used. Install sleeves during erection of walls. Cut sleeves to length for mounting flush with both surfaces of walls. Deburr after cutting.
 - 5. Install sleeves for floor penetrations. Extend sleeves installed in floors **1 inches (50 mm)** above finished floor level. Install sleeves during erection of floors.
- D. Sleeves for Conduits Penetrating Non-Fire-Rated Gypsum Board Assemblies:
 - 1. Use circular metal sleeves unless penetration arrangement requires rectangular sleeved opening.
 - 2. Seal space outside of sleeves with approved joint compound for gypsum board assemblies.
- E. Roof-Penetration Sleeves: Seal penetration of individual raceways and cables with flexible boot-type flashing units applied in coordination with roofing work.

- F. Aboveground, Exterior-Wall Penetrations: Seal penetrations using [steel] [cast-iron] pipe sleeves and mechanical sleeve seals. Select sleeve size to allow for 1-inch (25-mm) annular clear space between pipe and sleeve for installing mechanical sleeve seals.
- G. Underground, Exterior-Wall and Floor Penetrations: Install cast-iron pipe sleeves. Size sleeves to allow for 1-inch (25-mm) annular clear space between raceway or cable and sleeve for installing sleeve-seal system.

3.2 SLEEVE-SEAL-SYSTEM INSTALLATION

- A. Install sleeve-seal systems in sleeves in exterior concrete walls and slabs-on-grade at raceway entries into building.
- B. Install type and number of sealing elements recommended by manufacturer for raceway or cable material and size. Position raceway or cable in center of sleeve. Assemble mechanical sleeve seals and install in annular space between raceway or cable and sleeve. Tighten bolts against pressure plates that cause sealing elements to expand and make watertight seal.

3.3 SLEEVE-SEAL-FITTING INSTALLATION

- A. Install sleeve-seal fittings in new walls and slabs as they are constructed.
- B. Assemble fitting components of length to be flush with both surfaces of concrete slabs and walls. Position waterstop flange to be centered in concrete slab or wall.
- C. Secure nailing flanges to concrete forms.
- D. Using grout, seal the space around outside of sleeve-seal fittings.

END OF SECTION 260544

SECTION 260553 - IDENTIFICATION FOR ELECTRICAL SYSTEMS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:
 - 1. Color and legend requirements for raceways, conductors, and warning labels and signs.
 - 2. Labels.
 - 3. Bands and tubes.
 - 4. Tapes and stencils.
 - 5. Tags.
 - 6. Signs.
 - 7. Cable ties.
 - 8. Paint for identification.
 - 9. Fasteners for labels and signs.

1.3 ACTION SUBMITTALS

- A. Product Data: For each type of product.
 - 1. Include construction details, material descriptions, dimensions of individual components and profiles, and finishes for electrical identification products.
- B. Samples: For each type of label and sign to illustrate composition, size, colors, lettering style, mounting provisions, and graphic features of identification products.
- C. Identification Schedule: For each piece of electrical equipment and electrical system components to be an index of nomenclature for electrical equipment and system components used in identification signs and labels. Use same designations indicated on Drawings.
- D. Delegated-Design Submittal: For arc-flash hazard study.

PART 2 - PRODUCTS

2.1 PERFORMANCE REQUIREMENTS

- A. Comply with ASME A13.1 and IEEE C2.

- B. Comply with NFPA 70.
- C. Comply with 29 CFR 1910.144 and 29 CFR 1910.145.
- D. Comply with ANSI Z535.4 for safety signs and labels.
- E. Comply with NFPA 70E and Section 260574 "Overcurrent Protective Device Arc-Flash Study" requirements for arc-flash warning labels.
- F. Adhesive-attached labeling materials, including label stocks, laminating adhesives, and inks used by label printers, shall comply with UL 969.
- G. Thermal Movements: Allow for thermal movements from ambient and surface temperature changes.
 - 1. Temperature Change: 120 deg F (67 deg C), ambient; 180 deg F (100 deg C), material **surfaces**.

2.2 COLOR AND LEGEND REQUIREMENTS

- A. Raceways and Cables Carrying Circuits at 600 V or Less:
 - 1. **Black letters on an orange field.**
 - 2. Legend: Indicate voltage **and system or service type**.
- B. Color-Coding for Phase- and Voltage-Level Identification, 600 V or Less: Use colors listed below for ungrounded **service, feeder, and branch-circuit** conductors.
 - 1. Color shall be factory applied or field applied for sizes larger than No. 8 AWG if **authorities having jurisdiction permit**.
 - 2. Colors for 208/120-V Circuits:
 - a. Phase A: Black.
 - b. Phase B: Red.
 - c. Phase C: Blue.
 - 3. Colors for 240-V Circuits:
 - a. Phase A: Black.
 - b. Phase B: Red.
 - 4. Colors for 480/277-V Circuits:
 - a. Phase A: Brown.
 - b. Phase B: Orange.
 - c. Phase C: Yellow.
 - 5. Color for Neutral: **White**.
 - 6. Color for Equipment Grounds: **Bare copper, Green**.
 - 7. Colors for Isolated Grounds: Green with white stripe.

- C. Raceways and Cables Carrying Circuits at More Than 600 V:
 - 1. Black letters on an orange field.
 - 2. Legend: "DANGER - CONCEALED HIGH VOLTAGE WIRING."
- D. Warning Label Colors:
 - 1. Identify system voltage with black letters on an orange background.
- E. Warning labels and signs shall include, but are not limited to, the following legends:
 - 1. Multiple Power Source Warning: "DANGER - ELECTRICAL SHOCK HAZARD - EQUIPMENT HAS MULTIPLE POWER SOURCES."
 - 2. Workspace Clearance Warning: "WARNING - OSHA REGULATION - AREA IN FRONT OF ELECTRICAL EQUIPMENT MUST BE KEPT CLEAR FOR 36 INCHES (915 MM)."
 - 3. See project plans for additional signage requirements.
- F. Equipment Identification Labels:
 - 1. Black letters on a white field.

2.3 LABELS

- A. Vinyl Wraparound Labels: Preprinted, flexible labels laminated with a clear, weather- and chemical-resistant coating and matching wraparound clear adhesive tape for securing label ends.
- B. Snap-around Labels: Slit, pretensioned, flexible, preprinted, color-coded acrylic sleeves, with diameters sized to suit diameters and that stay in place by gripping action.
- C. Self-Adhesive Wraparound Labels: **Preprinted**, 3-mil- (0.08-mm-) thick **vinyl** flexible label with acrylic pressure-sensitive adhesive.
 - 1. Self-Lamination: Clear; UV-, weather- and chemical-resistant; self-laminating, protective shield over the legend. Labels sized such that the clear shield overlaps the entire printed legend.
 - 2. Marker for Labels: Permanent, waterproof, black ink marker recommended by tag manufacturer.
 - 3. Marker for Labels: Machine-printed, permanent, waterproof, black ink recommended by printer manufacturer.
- D. Self-Adhesive Labels: **Vinyl**, thermal, transfer-printed, 3-mil- (0.08-mm-) thick, multicolor, weather- and UV-resistant, pressure-sensitive adhesive labels, configured for intended use and location.
 - 1. Minimum Nominal Size:
 - a. 1-1/2 by 6 inches (37 by 150 mm) for raceway and conductors.
 - b. 3-1/2 by 5 inches (76 by 127 mm) for equipment.
 - c. As required by authorities having jurisdiction.

2.4 BANDS AND TUBES

- A. Snap-around, Color-Coding Bands: Slit, pretensioned, flexible, solid-colored acrylic sleeves, 2 inches (50 mm) long, with diameters sized to suit diameters and that stay in place by gripping action.
- B. Heat-Shrink Preprinted Tubes: Flame-retardant polyolefin tubes with machine-printed identification labels, sized to suit diameter and shrunk to fit firmly. Full shrink recovery occurs at a maximum of 200 deg F (93 deg C). Comply with UL 224.

2.5 TAPES AND STENCILS

- A. Marker Tapes: Vinyl or vinyl-cloth, self-adhesive wraparound type, with circuit identification legend machine printed by thermal transfer or equivalent process.
- B. Self-Adhesive Vinyl Tape: Colored, heavy duty, waterproof, fade resistant; not less than 3 mils (0.08 mm) thick by 1 to 2 inches (25 to 50 mm) wide; compounded for outdoor use.
- C. Tape and Stencil: 4-inch- (100-mm-) wide black stripes on 10-inch (250-mm) centers placed diagonally over orange background and is 12 inches (300 mm) wide. Stop stripes at legends.
- D. Floor Marking Tape: 2-inch- (50-mm-) wide, 5-mil (0.125-mm) pressure-sensitive vinyl tape, with [black and white] [yellow and black] stripes and clear vinyl overlay.

2.6 TAGS

- A. Metal Tags: Brass or aluminum, 2 by 2 by 0.05 inch (50 by 50 by 1.3 mm), with stamped legend, punched for use with self-locking cable tie fastener.
- B. Nonmetallic Preprinted Tags: Polyethylene tags, [0.015 inch (0.38 mm)] [0.023 inch (0.58 mm)] thick, color-coded for phase and voltage level, with factory [screened] [printed] permanent designations; punched for use with self-locking cable tie fastener.
- C. Write-on Tags:
 - 1. Polyester Tags: [0.010 inch (0.25 mm)] [0.015 inch (0.38 mm)] <Insert dimension> thick, with corrosion-resistant grommet and cable tie for attachment.
 - 2. Marker for Tags: Permanent, waterproof, black ink marker recommended by tag manufacturer.
 - 3. Marker for Tags: Machine-printed, permanent, waterproof, black ink marker recommended by printer manufacturer.

2.7 SIGNS

- A. Baked-Enamel Signs:
 - 1. Preprinted aluminum signs, punched or drilled for fasteners, with colors, legend, and size required for application.
 - 2. 1/4-inch (6.4-mm) grommets in corners for mounting.
 - 3. Nominal Size: 7 by 10 inches (180 by 250 mm).

- B. Metal-Backed Butyrate Signs:
 - 1. Weather-resistant, nonfading, preprinted, cellulose-acetate butyrate signs, with 0.0396-inch (1-mm) galvanized-steel backing, punched and drilled for fasteners, and with colors, legend, and size required for application.
 - 2. 1/4-inch (6.4-mm) grommets in corners for mounting.
 - 3. Nominal Size: 10 by 14 inches (250 by 360 mm).
- C. Laminated Acrylic or Melamine Plastic Signs:
 - 1. Engraved legend.
 - 2. Thickness:
 - a. For signs up to 20 sq. in. (129 sq. cm), minimum 1/16 inch (1.6 mm) thick.
 - b. For signs larger than 20 sq. in. (129 sq. cm), 1/8 inch (3.2 mm) thick.
 - c. Engraved legend with [black letters on white face] [white letters on a dark gray background] <Insert colors>.
 - d. [Punched or drilled for mechanical fasteners with 1/4-inch (6.4-mm) grommets in corners for mounting] [Self-adhesive].
 - e. Framed with mitered acrylic molding and arranged for attachment at applicable equipment.

2.8 CABLE TIES

- A. General-Purpose Cable Ties: Fungus inert, self-extinguishing, one piece, self-locking, and Type 6/6 nylon.
 - 1. Minimum Width: 3/16 inch (5 mm).
 - 2. Tensile Strength at 73 Deg F (23 Deg C) according to ASTM D 638: 12,000 psi (82.7 MPa).
 - 3. Temperature Range: Minus 40 to plus 185 deg F (Minus 40 to plus 85 deg C).
 - 4. Color: Black, except where used for color-coding.
- B. UV-Stabilized Cable Ties: Fungus inert, designed for continuous exposure to exterior sunlight, self-extinguishing, one piece, self-locking, and Type 6/6 nylon.
 - 1. Minimum Width: 3/16 inch (5 mm).
 - 2. Tensile Strength at 73 Deg F (23 Deg C) according to ASTM D 638: 12,000 psi (82.7 MPa).
 - 3. Temperature Range: Minus 40 to plus 185 deg F (Minus 40 to plus 85 deg C).
 - 4. Color: Black.
- C. Plenum-Rated Cable Ties: Self-extinguishing, UV stabilized, one piece, and self-locking.
 - 1. Minimum Width: 3/16 inch (5 mm).
 - 2. Tensile Strength at 73 Deg F (23 Deg C) according to ASTM D 638: 7000 psi (48.2 MPa).
 - 3. UL 94 Flame Rating: 94V-0.
 - 4. Temperature Range: Minus 50 to plus 284 deg F (Minus 46 to plus 140 deg C).
 - 5. Color: Black.

2.9 MISCELLANEOUS IDENTIFICATION PRODUCTS

- A. Paint: Comply with requirements in painting Sections for paint materials and application requirements. Retain paint system applicable for surface material and location (exterior or interior).
- B. Fasteners for Labels and Signs: Self-tapping, stainless-steel screws or stainless-steel machine screws with nuts and flat and lock washers.

PART 3 - EXECUTION

3.1 PREPARATION

- A. Self-Adhesive Identification Products: Before applying electrical identification products, clean substrates of substances that could impair bond, using materials and methods recommended by manufacturer of identification product.

3.2 INSTALLATION

- A. Verify and coordinate identification names, abbreviations, colors, and other features with requirements in other Sections requiring identification applications, Drawings, Shop Drawings, manufacturer's wiring diagrams, and operation and maintenance manual. Use consistent designations throughout Project.
- B. Install identifying devices before installing acoustical ceilings and similar concealment.
- C. Verify identity of each item before installing identification products.
- D. Coordinate identification with Project Drawings, manufacturer's wiring diagrams, and operation and maintenance manual.
- E. Apply identification devices to surfaces that require finish after completing finish work.
- F. Install signs with approved legend to facilitate proper identification, operation, and maintenance of electrical systems and connected items.
- G. System Identification for Raceways and Cables under 600 V: Identification shall completely encircle cable or conduit. Place identification of two-color markings in contact, side by side.
 - 1. Secure tight to surface of conductor, cable, or raceway.
- H. System Identification for Raceways and Cables over 600 V: Identification shall completely encircle cable or conduit. Place adjacent identification of two-color markings in contact, side by side.
 - 1. Secure tight to surface of conductor, cable, or raceway.
- I. Auxiliary Electrical Systems Conductor Identification: Identify field-installed alarm, control, and signal connections.

- J. Emergency Operating Instruction Signs: Install instruction signs with white legend on a red background with minimum 3/8-inch- (10-mm-) high letters for emergency instructions at equipment used for [power transfer] [load shedding] <Insert emergency operations>.
- K. Elevated Components: Increase sizes of labels, signs, and letters to those appropriate for viewing from the floor.
- L. Accessible Fittings for Raceways: Identify the covers of each junction and pull box of the following systems with the wiring system legend and system voltage. System legends shall be as follows:
 - 1. "EMERGENCY POWER."
 - 2. "POWER."
 - 3. "UPS."
- M. Vinyl Wraparound Labels:
 - 1. Secure tight to surface of raceway or cable at a location with high visibility and accessibility.
 - 2. Attach labels that are not self-adhesive type with clear vinyl tape, with adhesive appropriate to the location and substrate.
- N. Snap-around Labels: Secure tight to surface at a location with high visibility and accessibility.
- O. Self-Adhesive Wraparound Labels: Secure tight to surface at a location with high visibility and accessibility.
- P. Self-Adhesive Labels:
 - 1. On each item, install unique designation label that is consistent with wiring diagrams, schedules, and operation and maintenance manual.
 - 2. Unless otherwise indicated, provide a single line of text with 1/2-inch- (13-mm-) high letters on 1-1/2-inch- (38-mm-) high label; where two lines of text are required, use labels 2 inches (50 mm) high.
- Q. Snap-around Color-Coding Bands: Secure tight to surface at a location with high visibility and accessibility.
- R. Heat-Shrink, Preprinted Tubes: Secure tight to surface at a location with high visibility and accessibility.
- S. Marker Tapes: Secure tight to surface at a location with high visibility and accessibility.
- T. Self-Adhesive Vinyl Tape: Secure tight to surface at a location with high visibility and accessibility.
 - 1. Field-Applied, Color-Coding Conductor Tape: Apply in half-lapped turns for a minimum distance of 6 inches (150 mm) where splices or taps are made. Apply last two turns of tape with no tension to prevent possible unwinding.

- U. Tape and Stencil: Comply with requirements in painting Sections for surface preparation and paint application.
- V. Floor Marking Tape: Apply stripes to finished surfaces following manufacturer's written instructions.
- W. Metal Tags:
 - 1. Place in a location with high visibility and accessibility.
 - 2. Secure using **general-purpose** cable ties.
- X. Nonmetallic Preprinted Tags:
 - 1. Place in a location with high visibility and accessibility.
 - 2. Secure using **general-purpose** cable ties.
- Y. Write-on Tags:
 - 1. Place in a location with high visibility and accessibility.
 - 2. Secure using **general-purpose** cable ties.
- Z. Baked-Enamel Signs:
 - 1. Attach signs that are not self-adhesive type with mechanical fasteners appropriate to the location and substrate.
 - 2. Unless otherwise indicated, provide a single line of text with 1/2-inch- (13-mm-) high letters on minimum 1-1/2-inch- (38-mm-) high sign; where two lines of text are required, use signs minimum 2 inches (50 mm) high.
- AA. Metal-Backed Butyrate Signs:
 - 1. Attach signs that are not self-adhesive type with mechanical fasteners appropriate to the location and substrate.
 - 2. Unless otherwise indicated, provide a single line of text with 1/2-inch- (13-mm-) high letters on 1-1/2-inch- (38-mm-) high sign; where two lines of text are required, use labels 2 inches (50 mm) high.
- BB. Laminated Acrylic or Melamine Plastic Signs:
 - 1. Attach signs that are not self-adhesive type with mechanical fasteners appropriate to the location and substrate.
 - 2. Unless otherwise indicated, provide a single line of text with 1/2-inch- (13-mm-) high letters on 1-1/2-inch- (38-mm-) high sign; where two lines of text are required, use labels 2 inches (50 mm) high.
- CC. Cable Ties: General purpose, for attaching tags, except as listed below:
 - 1. Outdoors: UV-stabilized nylon.
 - 2. In Spaces Handling Environmental Air: Plenum rated.

3.3 IDENTIFICATION SCHEDULE

- A. Install identification materials and devices at locations for most convenient viewing without interference with operation and maintenance of equipment. Install access doors or panels to provide view of identifying devices.
- B. Identify conductors, cables, and terminals in enclosures and at junctions, terminals, pull points, and locations of high visibility. Identify by system and circuit designation.
- C. Concealed Raceways, Duct Banks, More Than 600 V, within Buildings: Tape and stencil. Stencil legend "DANGER - CONCEALED HIGH-VOLTAGE WIRING" with 3-inch- (75-mm-) high, black letters on 20-inch (500-mm) centers.
 - 1. Locate identification at changes in direction, at penetrations of walls and floors, and at [10-foot (3-m)] [30-foot (10-m)] maximum intervals.
- D. Accessible Raceways, 600 V or Less, for Service, Feeder, and Branch Circuits, More Than 30A and 120V to Ground: Identify with self-adhesive **vinyl tape applied in bands**.
 - 1. Locate identification at changes in direction, at penetrations of walls and floors, at 50-foot (15-m) maximum intervals in straight runs, and at 25-foot (7.6-m) maximum intervals in congested areas.
- E. Accessible Fittings for Raceways and Cables within Buildings: Identify the covers of each junction and pull box of the following systems with self-adhesive labels containing the wiring system legend and system voltage. System legends shall be as follows:
 - 1. "EMERGENCY POWER."
 - 2. "POWER."
 - 3. "UPS."
- F. Power-Circuit Conductor Identification, 600 V or Less: For conductors in vaults, pull and junction boxes, manholes, and handholes, use **snap-around labels** to identify the phase.
 - 1. Locate identification at changes in direction, at penetrations of walls and floors, at 50-foot (15-m) maximum intervals in straight runs, and at 25-foot (7.6-m) maximum intervals in congested areas.
- G. Control-Circuit Conductor Identification: For conductors and cables in pull and junction boxes, manholes, and handholes, use **self-adhesive labels** with the conductor or cable designation, origin, and destination.
- H. Control-Circuit Conductor Termination Identification: For identification at terminations, provide **self-adhesive labels** with the conductor designation.
- I. Workspace Indication: Apply **tape and stencil** to finished surfaces. Show working clearances in the direction of access to live parts. Workspace shall comply with NFPA 70 and 29 CFR 1926.403 unless otherwise indicated. Do not install at flush-mounted panelboards and similar equipment in finished spaces.

- J. Instructional Signs: Self-adhesive labels, including the color code for grounded and ungrounded conductors.
- K. Operating Instruction Signs: **Self-adhesive labels.**
- L. Emergency Operating Instruction Signs: **Self-adhesive labels** with white legend on a red background with minimum 3/8-inch- (10-mm-) high letters for emergency instructions at equipment used for **power transfer.**
- M. Equipment Identification Labels:
 - 1. Outdoor Equipment: **Laminated acrylic or melamine sign 4 inches (100 mm) high.**
 - 2. Equipment to Be Labeled:
 - a. Panelboards: Typewritten directory of circuits in the location provided by panelboard manufacturer. Panelboard identification shall be in the form of a [**self-adhesive, engraved,**] [**engraved,**] laminated acrylic or melamine label.
 - b. Enclosures and electrical cabinets.
 - c. Access doors and panels for concealed electrical items.
 - d. Switchgear.
 - e. Switchboards.
 - f. Transformers: Label that includes tag designation indicated on Drawings for the transformer, feeder, and panelboards or equipment supplied by the secondary.
 - g. Emergency system boxes and enclosures.
 - h. Motor-control centers.
 - i. Enclosed switches.
 - j. Enclosed circuit breakers.
 - k. Enclosed controllers.
 - l. Push-button stations.
 - m. Power-transfer equipment.
 - n. Contactors.
 - o. Remote-controlled switches, dimmer modules, and control devices.
 - p. Battery-inverter units.
 - q. Battery racks.
 - r. Power-generating units.
 - s. Monitoring and control equipment.

END OF SECTION 260553

SECTION 262213 - LOW-VOLTAGE DISTRIBUTION TRANSFORMERS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section includes distribution, dry-type transformers with a nominal primary and secondary rating of 600 V and less, with capacities up to 1500 kVA.

1.3 ACTION SUBMITTALS

- A. Product Data: For each type of product.
 - 1. Include construction details, material descriptions, dimensions of individual components and profiles, and finishes for each type and size of transformer.
 - 2. Include rated nameplate data, capacities, weights, dimensions, minimum clearances, installed devices and features, and performance for each type and size of transformer.
- B. Shop Drawings:
 - 1. Detail equipment assemblies and indicate dimensions, weights, loads, required clearances, method of field assembly, components, and location and size of each field connection.
 - 2. Vibration Isolation Base Details: Detail fabrication including anchorages and attachments to structure and to supported equipment.
 - 3. Include diagrams for power, signal, and control wiring.

1.4 INFORMATIONAL SUBMITTALS

- A. Qualification Data: For testing agency.
- B. Source quality-control reports.
- C. Field quality-control reports.

1.5 CLOSEOUT SUBMITTALS

- A. Operation and Maintenance Data: For transformers to include in emergency, operation, and maintenance manuals.

1.6 QUALITY ASSURANCE

- A. Testing Agency Qualifications: Accredited by NETA.
 - 1. Testing Agency's Field Supervisor: Certified by NETA to supervise on-site testing.

1.7 DELIVERY, STORAGE, AND HANDLING

- A. Inspection: On receipt, inspect for and note any shipping damage to packaging and transformer.
 - 1. If manufacturer packaging is removed for inspection, and transformer will be stored after inspection, re-package transformer using original or new packaging materials that provide protection equivalent to manufacturer's packaging.
- B. Storage: Store in a warm, dry, and temperature-stable location in original shipping packaging.
- C. Temporary Heating: Apply temporary heat according to manufacturer's written instructions within the enclosure of each ventilated-type unit, throughout periods during which equipment is not energized and when transformer is not in a space that is continuously under normal control of temperature and humidity.
- D. Handling: Follow manufacturer's instructions for lifting and transporting transformers.

PART 2 - PRODUCTS

2.1 MANUFACTURERS

- A. Source Limitations: Obtain each transformer type from single source from single manufacturer.

2.2 GENERAL TRANSFORMER REQUIREMENTS

- A. Description: Factory-assembled and -tested, air-cooled units for 60-Hz service.
- B. Comply with NFPA 70.
 - 1. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and use.
- C. Transformers Rated 15 kVA and Larger:
 - 1. Comply with 10 CFR 431 (DOE 2016) efficiency levels.
 - 2. Marked as compliant with DOE 2016 efficiency levels by an NRTL.
- D. Shipping Restraints: Paint or otherwise color-code bolts, wedges, blocks, and other restraints that are to be removed after installation and before energizing. Use fluorescent colors that are easily identifiable inside the transformer enclosure.

2.3 DISTRIBUTION TRANSFORMERS

- A. Comply with NFPA 70, **and list and label as complying with UL 1561.**
- B. Provide transformers that are constructed to withstand seismic forces specified in Section 260548.16 "Seismic Controls for Electrical Systems."
- C. Cores: Electrical grade, non-aging silicon steel with high permeability and low hysteresis losses.
 - 1. One leg per phase.
 - 2. Core volume shall allow efficient transformer operation at 10 percent above the nominal tap voltage.
 - 3. Grounded to enclosure.
- D. Coils: Continuous windings except for taps.
 - 1. Coil Material: **Copper.**
 - 2. Internal Coil Connections: Brazed or pressure type.
 - 3. Terminal Connections: **Bolted.**
- E. Encapsulation: Transformers smaller than 30 kVA shall have core and coils completely resin encapsulated.
- F. Enclosure: **Ventilated.**
 - 1. NEMA 250, **Type 3R:** Core and coil shall be encapsulated within resin compound **using a vacuum-pressure impregnation process** to seal out moisture and air.
 - 2. KVA Ratings: Based on convection cooling only and not relying on auxiliary fans.
 - 3. Wiring Compartment: Sized for conduit entry and wiring installation.
 - 4. Finish: Comply with NEMA 250.
 - a. Finish Color: **ANSI 61 gray** weather-resistant enamel.
- G. Taps for Transformers 3 kVA and Smaller: **None.**
- H. Taps for Transformers 7.5 to 24 kVA: **One 5 percent tap above and one 5 percent tap below normal full capacity.**
- I. Taps for Transformers 25 kVA and Larger: **Two 2.5 percent taps above and two 2.5 percent taps below normal full capacity.**
- J. Insulation Class, Smaller Than 30 kVA: 180 deg C, UL-component-recognized insulation system with a maximum of 115 deg C rise above 40 deg C ambient temperature.
- K. Insulation Class, 30 kVA and Larger: 220 deg C, UL-component-recognized insulation system with a maximum of **150** deg C rise above 40 deg C ambient temperature.
- L. Grounding: Provide ground-bar kit or a ground bar installed on the inside of the transformer enclosure.

- M. **K-Factor Rating:** Transformers indicated to be K-factor rated shall comply with UL 1561 requirements for nonsinusoidal load current-handling capability to the degree defined by designated K-factor.
 - 1. Unit shall not overheat when carrying full-load current with harmonic distortion corresponding to designated K-factor, without exceeding the indicated insulation class in a 40 deg C maximum ambient and a 24-hour average ambient of 30 deg C.
 - 2. Indicate value of K-factor on transformer nameplate.
 - 3. Unit shall comply with requirements of DOE 2016 efficiency levels when tested according to NEMA TP 2 with a K-factor equal to one.
- N. **Electrostatic Shielding:** Each winding shall have an independent, single, full-width copper electrostatic shield arranged to minimize interwinding capacitance.
 - 1. Arrange coil leads and terminal strips to minimize capacitive coupling between input and output terminals.
 - 2. Include special terminal for grounding the shield.
- O. **Neutral:** Rated 200 percent of full load current for K-factor-rated transformers.
- P. **Low-Sound-Level Requirements:** Maximum sound levels when factory tested according to IEEE C57.12.91, as follows:
 - 1. 9.00 kVA and Less: **40dBA**.
 - 2. 9.01 to 30.00 kVA: **45dBA**.
 - 3. 30.01 to 50.00 kVA: **45 dBA for K-factors of 1, 4, and 9**.
 - 4. 50.01 to 150.00 kVA: **50 dBA for K-factors of 1, 4, and 9**.
 - 5. 150.01 to 300.00 kVA: **55 dBA for K-factors of 1, 4, and 9**.
 - 6. 300.01 to 500.00 kVA: **60 dBA for K-factors of 1, 4, and 9**.
 - 7. 500.01 to 700.00: **62 dBA for K-factors of 1, 4, and 9**.
 - 8. 700.01 to 1000.00: **64 dBA for K-factors of 1, 4, and 9**.

2.4 IDENTIFICATION

- A. **Nameplates:** Engraved, laminated-acrylic or melamine plastic signs for each distribution transformer, mounted with corrosion-resistant screws. Nameplates and label products are specified in Section 260553 "Identification for Electrical Systems."
- B. **Nameplates:** Self-adhesive label for each distribution transformer. Self-adhesive labels are specified in Section 260553 "Identification for Electrical Systems."

2.5 SOURCE QUALITY CONTROL

- A. **Test and inspect transformers according to IEEE C57.12.01 and IEEE C57.12.91.**
 - 1. Resistance measurements of all windings at rated voltage connections and at all tap connections.
 - 2. Ratio tests at rated voltage connections and at all tap connections.

3. Phase relation and polarity tests at rated voltage connections.
4. No load losses, and excitation current and rated voltage at rated voltage connections.
5. Impedance and load losses at rated current and rated frequency at rated voltage connections.
6. Applied and induced tensile tests.
7. Regulation and efficiency at rated load and voltage.
8. Insulation-Resistance Tests:
 - a. High-voltage to ground.
 - b. Low-voltage to ground.
 - c. High-voltage to low-voltage.
9. Temperature tests.

B. **Factory Sound-Level Tests: Conduct prototype sound-level tests on production-line products.**

PART 3 - EXECUTION

3.1 EXAMINATION

- A. Examine conditions for compliance with enclosure- and ambient-temperature requirements for each transformer.
- B. Verify that field measurements are as needed to maintain working clearances required by NFPA 70 and manufacturer's written instructions.
- C. Examine walls, floors, roofs, and concrete bases for suitable mounting conditions where transformers will be installed.
- D. Verify that ground connections are in place and requirements in Section 260526 "Grounding and Bonding for Electrical Systems" have been met. Maximum ground resistance shall be 5 ohms at location of transformer.
- E. Environment: Enclosures shall be rated for the environment in which they are located. Covers for NEMA 250, Type 4X enclosures shall not cause accessibility problems.
- F. Proceed with installation only after unsatisfactory conditions have been corrected.

3.2 INSTALLATION

- A. Install transformers level and plumb on a concrete base with vibration-dampening supports. Locate transformers away from corners and not parallel to adjacent wall surface.
- B. Construct concrete bases according to project plans and anchor floor-mounted transformers according to manufacturer's written instructions and requirements in Section 260529 "Hangers and Supports for Electrical Systems."

1. Coordinate size and location of concrete bases with actual transformer provided. Cast anchor-bolt inserts into bases. Concrete, reinforcement, and formwork requirements are specified with concrete.
- C. Secure transformer to concrete base according to manufacturer's written instructions.
- D. Secure covers to enclosure and tighten all bolts to manufacturer-recommended torques to reduce noise generation.
- E. Remove shipping bolts, blocking, and wedges.

3.3 CONNECTIONS

- A. Ground equipment according to Section 260526 "Grounding and Bonding for Electrical Systems."
- B. Connect wiring according to Section 260519 "Low-Voltage Electrical Power Conductors and Cables."
- C. Tighten electrical connectors and terminals according to manufacturer's published torque-tightening values. If manufacturer's torque values are not indicated, use those specified in UL 486A-486B.
- D. Provide flexible connections at all conduit and conductor terminations and supports to eliminate sound and vibration transmission to the building structure.

3.4 FIELD QUALITY CONTROL

- A. Testing Agency: Owner will engage a qualified testing agency to perform tests and inspections.
- B. Testing Agency: Engage a qualified testing agency to perform tests and inspections.
- C. Manufacturer's Field Service: Engage a factory-authorized service representative to test and inspect components, assemblies, and equipment installations, including connections.
- D. Perform tests and inspections.
- E. Small (Up to 167-kVA Single-Phase or 500-kVA Three-Phase) Dry-Type Transformer Field Tests:
 1. Visual and Mechanical Inspection.
 - a. Inspect physical and mechanical condition.
 - b. Inspect anchorage, alignment, and grounding.
 - c. Verify that resilient mounts are free and that any shipping brackets have been removed.
 - d. Verify the unit is clean.
 - e. Perform specific inspections and mechanical tests recommended by manufacturer.
 - f. Verify that as-left tap connections are as specified.
 - g. Verify the presence of surge arresters and that their ratings are as specified.

2. Electrical Tests:
 - a. Measure resistance at each winding, tap, and bolted connection.
 - b. Perform insulation-resistance tests winding-to-winding and each winding-to-ground. Apply voltage according to manufacturer's published data. In the absence of manufacturer's published data, comply with NETA ATS, Table 100.5. Calculate polarization index: the value of the index shall not be less than 1.0.
 - c. Perform turns-ratio tests at all tap positions. Test results shall not deviate by more than one-half percent from either the adjacent coils or the calculated ratio. If test fails, replace the transformer.
 - d. Verify correct secondary voltage, phase-to-phase and phase-to-neutral, after energization and prior to loading.
- F. Large (Larger Than 167-kVA Single Phase or 500-kVA Three Phase) Dry-Type Transformer Field Tests:
1. Visual and Mechanical Inspection:
 - a. Inspect physical and mechanical condition.
 - b. Inspect anchorage, alignment, and grounding.
 - c. Verify that resilient mounts are free and that any shipping brackets have been removed.
 - d. Verify the unit is clean.
 - e. Perform specific inspections and mechanical tests recommended by manufacturer.
 - f. Verify that as-left tap connections are as specified.
 - g. Verify the presence of surge arresters and that their ratings are as specified.
 2. Electrical Tests:
 - a. Measure resistance at each winding, tap, and bolted connection.
 - b. Perform insulation-resistance tests winding-to-winding and each winding-to-ground. Apply voltage according to manufacturer's published data. In the absence of manufacturer's published data, comply with NETA ATS, Table 100.5. Calculate polarization index: the value of the index shall not be less than 1.0.
 - c. Perform power-factor or dissipation-factor tests on all windings.
 - d. Perform turns-ratio tests at all tap positions. Test results shall not deviate by more than one-half percent from either the adjacent coils or the calculated ratio. If test fails, replace the transformer.
 - e. Perform an excitation-current test on each phase.
 - f. Perform an applied voltage test on all high- and low-voltage windings to ground. See IEEE C57.12.91, Sections 10.2 and 10.9.
 - g. Verify correct secondary voltage, phase-to-phase and phase-to-neutral, after energization and prior to loading.
- G. Remove and replace units that do not pass tests or inspections and retest as specified above.
- H. Infrared Scanning: Two months after Substantial Completion, perform an infrared scan of transformer connections.
1. Use an infrared-scanning device designed to measure temperature or detect significant deviations from normal values. Provide documentation of device calibration.

2. Perform two follow-up infrared scans of transformers, one at four months and the other at 11 months after Substantial Completion.
 3. Prepare a certified report identifying transformer checked and describing results of scanning. Include notation of deficiencies detected, remedial action taken, and scanning observations after remedial action.
- I. Test Labeling: On completion of satisfactory testing of each unit, attach a dated and signed "Satisfactory Test" label to tested component.

3.5 ADJUSTING

- A. Record transformer secondary voltage at each unit for at least 48 hours of typical occupancy period. Adjust transformer taps to provide optimum voltage conditions at secondary terminals. Optimum is defined as not exceeding nameplate voltage plus 5 percent and not being lower than nameplate voltage minus 3 percent at maximum load conditions. Submit recording and tap settings as test results.
- B. Output Settings Report: Prepare a written report recording output voltages and tap settings.

3.6 CLEANING

- A. Vacuum dirt and debris; do not use compressed air to assist in cleaning.

END OF SECTION 262213

SECTION 262313 - PARALLELING LOW-VOLTAGE SWITCHGEAR

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes: Metal-enclosed, low-voltage, circuit-breaker switchgear rated 600 V and less, and associated monitoring and control systems for paralleling standby generators on an isolated bus and for distributing electrical power.
- B. As applied to the TBPPs this switchgear is to be used when aggregating together two or more TBPPs to arrive at a given kW output. This aggregation will be for paralleling two or three TBPPs to the same emergency supply bus.
- C. Related Requirements:
 - 1. Section 263213.16 "Gaseous Emergency Engine Generators"
 - 2. Section 263373 "BESS"

1.3 DEFINITIONS

- A. ATS: Acceptance Testing Specification.
- B. DDC: Direct digital control.
- C. Legally Required: As used in this Section, it shall have the same meaning as used in NFPA 70.

1.4 ACTION SUBMITTALS

- A. Product Data: For each type of paralleling low-voltage switchgear.
 - 1. Include technical data on features, performance, electrical characteristics, ratings, and finishes for programmable logic controllers, instrumentation, control devices, monitoring devices, **SCADA interface devices**, **Ethernet interface**, and display components.
 - 2. Include rated capacities, operating characteristics, furnished specialties, factory settings, and accessories for individual circuit breakers.
 - 3. Include time-current characteristic curves for overcurrent protective devices.
- B. Shop Drawings: For each type of paralleling low-voltage switchgear.

1. Include dimensioned plans, elevations, sections, details, shipping sections, weights of each assembled section, and required clearances and service space around equipment.
 2. Include tabulation of installed devices with features and ratings.
 3. Include enclosure types and details.
 4. Detail locations for anchor bolts **and leveling channels**.
 5. Show bus configuration with current rating, size, and number of conductors in each bus run, including phase, neutral, and ground conductors of main and branch buses.
 6. Indicate short-time and short-circuit current rating of switchgear assembly.
 7. Include features, characteristics, ratings, and factory settings of individual overcurrent protective devices and auxiliary components.
 8. Detail nameplate legends.
 9. Include mimic-bus diagram.
 10. Include three-line power wiring diagrams for paralleling low-voltage switchgear, generators, and related equipment showing device terminal numbers.
 11. Include point-to-point schematic control, monitoring, and alarm wiring diagrams showing internal component terminal numbers.
 12. Include point-to-point schematic control, monitoring, and alarm wiring diagrams for external components indicating terminal numbers for the following:
 - a. Engine generators.
 - b. Transfer switches.
 - c. Other load-control devices.
 - d. Elevator controller in each elevator bank.
 - e. DDC system for HVAC controller.
 - f. SCADA remote terminal unit.
- C. Samples: Representative portion of mimic bus with specified finish. Manufacturer's color charts showing colors available for mimic bus.
- D. Delegated-Design Submittal: For paralleling low-voltage switchgear.
1. Include design calculations, signed and sealed by a qualified professional engineer, for selecting seismic restraints and for structural analysis of outdoor enclosures, including wind loading.
- E. Sequence of Operation: Description of sequence of operation for paralleling controls in automatic, manual, system test, and peak-shaving modes.
1. Include the following in the description of the automatic-mode sequence of operation:
 - a. Programmed sequence of initial generator starting and connection of generators to the isolated paralleling bus, including a description of how the proposed design complies with the requirements for redundancy.
 - b. Programmed sequence of transferring loads to the isolated paralleling bus based on operator-adjustable preset priorities and preset loads. Include initial load settings.
 - c. Programmed sequence of starting and stopping generators based on actual real-time measured loads.
 - d. Programmed sequence of sending a load-shed signal to transfer switches[, **and to other devices**] when the generator frequency does not return to the normal frequency within the adjustable time period.

- e. Programmed sequence of stopping generators based on no transfer switch or other device sending a start signal.
- 2. Include the following in the description of the system testing mode sequence of operation:
 - a. Load.
 - b. No load.
- 3. Include in the description, the manual-mode sequence of operation showing that the manual mode fulfills the requirement to permit the operator at the paralleling low-voltage switchgear to accomplish all automatic, system test, and peak-shaving functions.
- 4. Paralleling Low-Voltage Switchgear Redundancy: Identify any single points of failure.

1.5 INFORMATIONAL SUBMITTALS

A. Coordination Drawings:

- 1. Floor plans showing dimensioned layout, required working clearances, and required area above and around paralleling low-voltage switchgear where pipe and ducts are prohibited.
- 2. Switchgear layout and relationships between components and adjacent structural and mechanical elements.
- 3. Support locations, type of support, and weight on each support. Indicate field measurements.

B. Qualification Data: For testing agency.

C. Source quality-control reports.

D. Field quality-control reports.

E. Sample Warranty: For manufacturer's special warranty.

1.6 CLOSEOUT SUBMITTALS

A. Updated mimic bus diagram reflecting field changes after final switchgear load connections have been made, for record.

B. Operation and Maintenance Data: For paralleling low-voltage switchgear and components to include in emergency, operation, and maintenance manuals.

- 1. In addition to items specified in Section 017823 "Operation and Maintenance Data," include the following:
 - a. Manufacturer's written instructions for sequence of operation.
 - b. Manufacturer's system checklists, maintenance schedule, and maintenance log sheets complying with NFPA 110.
 - c. Manufacturer's written instructions for testing and adjusting relays.
 - d. Time-current curves, including selectable ranges for each type of overcurrent protective device.

1.7 MAINTENANCE MATERIAL SUBMITTALS

- A. Furnish extra materials that match products installed and that are packaged with protective covering for storage and identified with labels describing contents.
 - 1. Control Power Fuses: **Six** of each type and rating used. Include spares for the following:
 - a. Potential transformers.
 - b. Control power circuits.
 - 2. Indicating Lights: **Six** of each type installed.
 - 3. Draw-out Circuit Breakers: One of each type and rating used for circuit breaker in the paralleling low-voltage switchgear.
- B. Maintenance Tools: Furnish tools and miscellaneous items required for paralleling low-voltage switchgear test, inspection, maintenance, and operation. Include the following:
 - 1. **Floor-running transport or dockable dolly with manual lifting mechanism** and all other items necessary to remove circuit breaker from housing and transport it to remote location.
 - 2. Racking handle to move circuit breaker manually between connected and disconnected positions.

1.8 QUALITY ASSURANCE

- A. Testing Agency Qualifications: Member company of NETA or an NRTL.
 - 1. Testing Agency's Field Supervisor: Currently certified by NETA to supervise on-site testing.

1.9 DELIVERY, STORAGE, AND HANDLING

- A. Deliver paralleling low-voltage switchgear in sections of lengths that can be moved past obstructions in delivery path.
- B. Store paralleling low-voltage switchgear indoors in clean dry space with uniform temperature to prevent condensation.

1.10 FIELD CONDITIONS

- A. Installation Pathway: Remove and replace building components and structures to provide pathway for moving paralleling low-voltage switchgear into place.
- B. Interruption of Existing Electrical Service: Do not interrupt electrical service to facilities occupied by Owner or others unless permitted under the following conditions and then only after arranging to provide temporary electrical service according to requirements indicated:
 - 1. Notify **Construction Manager** and **Owner** no fewer than five days in advance of proposed interruption of electrical service.

2. Do not proceed with interruption of electrical service without **Construction Manager's** and **Owner's** written permission.
- C. Environmental Limitations: Rate equipment for continuous operation at indicated ampere ratings for the following conditions:
1. Ambient temperature not exceeding **122 deg F (50 deg C)**.
 2. Altitude of 6600 feet above sea level.

1.11 WARRANTY

- A. **Manufacturer's Warranty:** Manufacturer agrees to repair or replace paralleling equipment that fails in materials or workmanship within specified warranty period.
1. Warranty Period: **Two** year(s) from date of Substantial Completion.

PART 2 - PRODUCTS

2.1 SYSTEM DESCRIPTION

- A. **Electrical Components, Devices, and Accessories:** Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and application.
- B. **Product Selection for Restricted Space:** Drawings indicate maximum dimensions for paralleling low-voltage switchgear, including clearances between paralleling switchgear and adjacent surfaces and other items. Comply with indicated maximum dimensions.
- C. The multiple-generator paralleling monitoring and control panel in the paralleling low-voltage switchgear shall monitor and control the following standby power system components:
1. Paralleling low-voltage switchgear.
 2. Engine generators.
 3. Transfer switches.
 4. Other load-control devices.
 5. Distribution circuit breakers in paralleling low-voltage switchgear.
- D. **Sequence of Operation for Normal Conditions:**
1. Paralleling low-voltage switchgear, including controlled generators, **controlled circuit breakers**, and transfer switches, shall be in the automatic position and ready to operate on loss of power or other designated initiation conditions.
 2. Each single-generator monitoring and control system has not received a "start" signal from the following:
 - a. Transfer switch.
 - b. Multiple-generator paralleling monitoring and control system.
 - c. Aggregation switchboard shall be energized through grid forming BESS systems from the aggregated TBPPs. All BESS systems shall be prior synchronized to form an aggregated output equal to the rating of the aggregated TBPPs.

E. Sequence of Operation for Loss of Normal Power Conditions:

1. System ATS shall transfer to already energized aggregation switchboard.
2. ATS shall send start signal to each engine generator in the aggregated TBPP.
3. On receiving a start signal, each single-generator monitoring and control system shall start engine generators and achieve rated voltage and frequency.
4. Black-Start Control: Prevent out-of-phase paralleling. After selecting the first generator to achieve 90 percent rated voltage and frequency, inhibit the connection of generator-controlled circuit breakers to the isolated paralleling bus, then close the circuit breaker connecting the first generator to the isolated paralleling bus.
 - a. Comply with requirements in Section 263213 "Engine Generators" for selection of the first engine generator to connect to the isolated paralleling bus.
5. Each single-generator paralleling monitoring and control system synchronizes its associated engine generator and allows closure of respective generator paralleling low-voltage circuit breakers to the isolated paralleling bus. On closure to isolated paralleling bus, each engine generator assumes its proportional share of total load.
6. Failure of an Engine Generator to Synchronize: If engine generator fails to synchronize, sound an alarm after a preset time delay, but continue to attempt to synchronize the engine generator until signaled to stop by manual operation.

F. Load-Demand Sequence of Operation:

1. With load-demand sequence of operation activated, controller continuously monitors total isolated paralleling bus load.
2. If isolated paralleling bus load is below preset limits and after a preset time delay, demand controller shuts down engine generators in predetermined order until minimum number of sets are operating. Set preset limits, predetermined order, and preset time delay, as well as choose manual operation, from human-machine interface.
3. On sensing available isolated paralleling bus capacity diminished to set point, controller starts and closes engine generators to isolated paralleling bus to accommodate load.

G. Individual Transfer Switch Return to Normal Condition Sequence of Operation: Enable individual transfer switches to return to normal power when normal power is available at the transfer switch.

1. When transfer is complete ATS sends stop signal to all generators.
2. BESS to remain energized and on isolated emergency bus.

H. System Test Sequence of Operation:

1. Configure tests to comply with NFPA 110, Level 1 testing requirements for each generator. Automatically generate NFPA 110, Level 1 reports.
2. Single-generator test.
3. Multiple-generator test.
4. Start generators manually, by generator exerciser on user-defined schedule.
5. Engine generator(s) start and achieve rated voltage and frequency.

6. Failure of Engine Generator to Start: After expiration of overcrank time delay, engine generator shuts down and alarm is initiated.
7. Black-Start Control: Prevent out-of-phase paralleling. After selecting first generator to achieve 90 percent rated voltage and frequency, inhibit connection of generator-controlled circuit breakers to isolated paralleling bus, then close circuit breaker connecting first generator to isolated paralleling bus. Each single-generator paralleling monitoring and control system synchronizes its associated engine generator and allows closure of respective generator paralleling low-voltage circuit breakers to the isolated paralleling bus. On closure to isolated paralleling bus, each engine generator assumes its proportional share of total load.
8. Failure of Engine Generator to Synchronize: If engine generator fails to synchronize, sound alarm after preset time delay, but continue to attempt to synchronize engine generator until signaled to stop by manual operation.
9. Manually select or automatically preselect whether test is a load or no-load test. If test is a load test, manually select or automatically preselect loads to be transferred according to schedule or by adjustable time delays at transfer switches. After generators are connected to isolated paralleling bus, transfer loads by sending signal to load-add relay that is connected to input for "remote transfer to generator source" of transfer switch controller or to other devices.
10. After adjustable period of time the system, allow engine generators to optimize down to only the required number to be online to avoid wet stacking. Set stopping and starting sequences through human-machine interface panel device and allow settings based on manual priorities or by engine run time.
11. On sensing available bus capacity diminished to set point, controller starts and closes engine generators to the isolated paralleling bus to accommodate load.
12. After system test is completed, transfer loads back to normal power with transfer switches. Shut down system using sequence in automatic mode.
13. If there is an outage during this mode of operation, automatically change to requirements specified in "Sequence of Operation for Loss of Normal Power Conditions" Paragraph, send load-shed signals to lower-priority loads until load is below generator capacity, signal any engine generator that is not currently operating to start, and cancel system test.

I. Comply with NFPA 110 for the following:

1. Emergency: EPSS Level 1, Type 10.
2. Legally Required Standby: EPSS Level 1, Type 60.
3. Optional Standby: EPSS [Level 1] [Level 2], [Type 10] [Type 60] [Type 120] [Manual].

J. Comply with NFPA 99 for healthcare applications.

2.2 MULTIPLE-GENERATOR PARALLELING MONITORING AND CONTROL SYSTEM

- A. Source Limitations: Obtain paralleling low-voltage switchgear from same manufacturer as required **transfer switches and engine generators**.
- B. Components and Devices: Factory mounted in a **metal-enclosed, paralleling low-voltage switchgear**.
 1. Paralleling Low-Voltage Switchgear Door-Mounted Control Devices: Industrial, oil-type devices.

2. Indicator Lamps: High-intensity digital display.
- C. Control Power for Multiple-Generator Monitoring and Control System: Supplied from 24-V dc starting batteries of engine generators.
1. Isolate each battery bank to prevent failure of one battery from disabling entire system.
 2. Include, if necessary, separate control power battery system rated 24-V dc for equipment unable to accept voltage drop that occurs during engine cranking.
- D. Multiple-generator monitoring and control system auto/manual selector switch.
- E. Full-Color, Touch-Screen, Human-Machine Interface Device:
1. Minimum viewing area of **60 sq. in. (387 sq. cm)** shall be configurable in either U.S. standard or SI (metric) units.
 2. Main Menu: Include date, time, and system status messages. Configure screens so that no screen is more than three touches from any other screen.
 - a. Individual engine generator data shall be accessed at the paralleling low-voltage switchgear from the **main menu and each single-generator paralleling monitoring and control system**.
 3. One-Line Diagram: Depicting system configuration and system status by screen animation, screen colors, text messages, or pop-up indicators.
 - a. Conditions for Engine Generators, Buses, and Paralleling Circuit Breakers: Energized or de-energized.
 - b. Engine Generator Modes:
 - 1) Auto.
 - 2) Lockout.
 - 3) Reset.
 - 4) Off.
 - 5) Cool down.
 - 6) Test off line.
 - 7) Test on load.
 - c. Engine Generator Status: Normal, warning, shutdown, or load-demand stop.
 - d. Paralleling Circuit-Breaker Status: Open, closed, or tripped.
 - e. Bus Conditions: Energized or de-energized.
 - f. Percent load.
 4. AC metering screen for isolated paralleling bus shall display the following:
 - a. Phase, volts, and amperes.
 - b. Kilowatts.
 - c. Kilovolt amperes.
 - d. Kilovolt-ampere rating.
 - e. Power factor.
 - f. Frequency.
 - g. Kilowatt hour.

- h. Kilowatt demand.
 - i. Real-time trend chart for system kilowatts and volts updated on not less than one-second intervals.
 - j. A minimum of one historical trend chart for total system loads with intervals no shorter than five minutes and a minimum duration of four hours.
 - k. Percent of available capacity of the engine generators that are operating in parallel on the bus.
5. Engine Generator Monitoring and Control Screen:
- a. Control:
 - 1) Engine generator manual start/stop control (functional only when the paralleling low-voltage switchgear mounted control switch is in "Auto" position).
 - 2) Engine generator alarm reset.
 - 3) Manual paralleling and circuit-breaker enable/inhibit controls.
 - 4) Engine function and timer settings.
 - 5) System function, testing, and timer settings.
 - 6) Engine generator optimization settings: automatically determine the priority of the engine generators based on engine run time and number of engine starts or manually assign engine priorities.
 - b. Status and Alarms:
 - 1) Power Metering: Watts, volt-ampere reactive, power factor, frequency, amperes, and voltage.
 - 2) Engine run hours.
 - 3) Engine status.
 - 4) Number of generator circuit-breaker operations.
 - 5) Replicate status and alarms from each single-generator paralleling monitoring and control panel.
6. Dual, Three-Phase, Metering Screen: Graphical analog (270 electrical degree) metering representation with digital display. Display two generators at the same time or one generator and the isolated paralleling bus at the same time. Display graphical synchroscope when one generator and the isolated paralleling bus are selected.
- a. True rms, three-phase voltage, amperes, kilowatts, kilovolt amperes, kilovolt-ampere reactive, power factor, and frequency parameters.
 - b. Engine battery voltage display.
7. Password-Protected System Control Screen:
- a. System Test Modes: Test with load/test without load/normal/retransfer time-delay override.
 - b. Test with Load: Starts and synchronizes engine generators on isolated paralleling bus; all loads are transferred to the isolated paralleling bus.
 - c. Test without Load: Starts and synchronizes engine generators on isolated paralleling bus but does not transfer loads to the isolated paralleling bus.

- d. Time adjustments for retransfer time delay, transfer time delay, system time delay on stopping, and system time delay on starting.
- 8. Load-Demand Control Screen: Monitors total load on the isolated paralleling bus and controls number of engine generators running so that capacity tracks load demand.
 - a. Load-Demand Control: Enable/disable.
 - b. Set engine generator shutdown sequence.
 - c. Load-Demand Pickup Set Point: Adjustable from 90 to 40 percent in 5 percent increments.
 - d. Load-Demand Dropout Set Point: Adjustable from 20 to 70 percent in 5 percent increments.
- 9. Alarm Summary and Run Report Screen:
 - a. Lists most recent alarm conditions and status changes.
 - b. Lists a minimum of the most recent 32 alarm conditions by name and time/date; acknowledges alarm conditions with time/date.
 - c. For each start signal, lists start time and date, stop time and date, maximum kilowatt and ampere load on system during run time, and start and stop times of individual engine generators.
 - d. Lists generator circuit position and status.
 - e. Access to trend all monitored automatic transfer switches.
 - f. **16-gigabyte** hard-disk space for storing the database file for multiple-generator paralleling monitoring and control panel trending and event logging. Trend and log data at a resolution of one second. If hard drive is full, overwrite in a first-in-first-out procedure.
 - 1) Trend up to eight monitored points simultaneously.
- 10. Load Status and Control Screen: Displays status of automatic transfer switches connected to the system for 6 transfer switches, and other controlled devices.
 - a. Automatic transfer switch connected to normal.
 - b. Automatic transfer switch connected to emergency.
 - c. Engine start indication.
 - d. Transfer Switch Power Metering Function: Total kilowatt, three-phase current, and three-phase voltage.
 - e. Automatic Transfer Switch Load Priority: Ability to change priorities of automatic transfer switches (password protected).
 - f. Display name, status, and priority of each load block (whether on or off) and the total load of that block.
- 11. Automated email messages shall be transmitted when shutdowns occur and shall include time and date of alarm.
- 12. Based on either the number operations or the time since the last maintenance, suggest maintenance period for generator (run hours), controlled circuit breaker (number of operations), and transfer switches (number of transfers).
- 13. Status and Alarm Screen:

- a. Visual alarm status indicator and alarm horn with silence and acknowledge push button.
- b. Status, Light Only:
 - 1) "SYSTEM NOT IN AUTO" (red).
 - 2) Running Status: Display engine generator number and running-status light (green).
 - 3) Load-demand mode (green).
 - 4) System test (green).
 - 5) Remote system start (red).
 - 6) Monitoring of Each Transfer Switch:
 - a) Normal source available for each (green).
 - b) Connected to normal (green).
 - c) Generator source available (green).
 - d) Connected to generator source (green).
- c. Status Light and Alarm:
 - 1) Isolated paralleling bus under frequency (red).
 - 2) Isolated paralleling bus over frequency (red).
 - 3) Auxiliary power failure (red).
 - 4) Emergency start signal power failure (red).
 - 5) Load-Shed Level Status: Displays load number and red load-shed, status light.
 - 6) Generator Alarm Status: Displays generator number and red "Check Generator" status light.
 - 7) Controller malfunction (red).
 - 8) Check station battery (red).
 - 9) Isolated paralleling bus overload (red).
 - 10) System not in auto (red).
 - 11) Main tank, low fuel (amber)
 - 12) Main tank, high fuel (amber).
 - 13) Main tank, fuel leak (red).

F. Remote Monitoring: Replicate human-machine interface monitoring functions **at remote computer terminal**.

G. Remote Monitoring of Status and Alarms: Replicate human-machine interface status and alarms at DDC system for HVAC via isolated contacts.

2.3 METAL-ENCLOSED, CIRCUIT-BREAKER SWITCHGEAR (600 V AND LESS)

- A. Source Limitations: Obtain paralleling low-voltage switchgear from same manufacturer as required for **transfer switches and engine generators**.
- B. Description: Factory assembled and tested, and complying with IEEE C37.20.1 and UL 1558.
- C. Ratings: Suitable for application in three-phase, 60-Hz, solidly grounded neutral system.
- D. Nominal System Voltage: Per project plans wire, 60 Hz.

- E. Isolated Paralleling Bus: Per project plans.
 - 1. Phase-, Neutral-, and Ground-Bus Materials:
 - a. Phase and Neutral Bus: **Copper, tin plated.**
 - b. Ground Bus: Copper, **tin** plated; minimum size 1/4 by 2 inches (6 by 50 mm).
 - 2. Bus bars connect between vertical sections and between compartments. Cable connections are not permitted.
 - a. Uniform capacity for horizontal and vertical bus.
 - b. Neutral Bus: **100** percent of phase-bus ampacity, except as indicated
 - c. Supports and Bracing for Buses: Adequate strength for indicated short-circuit currents.
- F. Short-Circuit Current: Match rating of highest-rated circuit breaker in switchgear assembly.
- G. Switchgear Fabrication:
 - 1. Bus isolation barriers shall be arranged to isolate line bus from load bus at each main and tie circuit breaker.
 - 2. Circuit-breaker compartments shall be equipped to house drawout-type circuit breakers and shall be fitted with hinged outer doors.
 - 3. Auxiliary Compartments: Match and align with basic switchgear assembly.
 - a. Bus transition sections.
 - b. Pull sections.
 - c. Hinged front panels for access to accessory and blank compartments.
 - d. Pull box on top of switchgear for extra room for pulling cable, with removable top, front, and side covers; and ventilation provisions adequate to maintain air temperature in pull box within same limits as switchgear.
 - 1) Set pull box back from front to clear circuit-breaker lifting mechanism.
 - 2) Bottom: Insulating, fire-resistive material with separate holes for cable drops into switchgear.
 - 3) Cable Supports: Arranged to ease cabling and adequate to support cables indicated, including those for future installation.
 - e. Neutral Disconnect Link: Bolted, uninsulated, 1/4-by-2-inch (6-by-50-mm) copper bus, arranged to connect neutral bus to ground bus.
 - f. Provide for future extensions from either end of main phase, neutral, and ground bus by means of predrilled bolt-holes and connecting links.
 - g. Bus-Bar Insulation: Individual bus bars wrapped with factory-applied, flame-retardant tape or spray-applied, flame-retardant insulation.
 - 1) Sprayed Insulation Thickness: 3 mils (0.08 mm), minimum.
 - 2) Bolted Bus Joints: Insulate with secure joint covers that can easily be removed and reinstalled.

4. Circuit-Breaker Terminals for Cable Connections: Silver-plated copper bus extensions equipped with pressure connectors for conductors.
- H. Circuit Breakers: Comply with IEEE C37.13, IEEE C37.16, and IEEE C37.17.
1. Ratings: As indicated on project plans for continuous, interrupting, and short-time current ratings for each circuit breaker; voltage and frequency ratings same as switchgear.
 2. Operating Mechanism: Mechanically and electrically trip-free, stored-energy operating mechanism with the following features:
 - a. Normal Closing Speed: Independent of both control and operator.
 - b. Slow Closing Speed: Optional with operator for inspection and adjustment.
 3. Stored-Energy Mechanism: Electrically charged, with optional manual charging **and operation counter**.
 4. Trip Devices:
 - a. Solid-state, overcurrent trip-device system consisting of one or two current transformers or sensors per phase, and a release mechanism.
 - b. Functions: Long-time-delay, short-time-delay, and instantaneous-trip functions, independent of each other in both action and adjustment.
 - c. Temperature Compensation: Ensures accuracy and calibration stability from minus 5 to plus 40 deg C.
 - d. Time-Current Characteristics: Field adjustable.
 - e. Current Adjustability: Dial settings and rating plugs on trip units or sensors on circuit breakers, or a combination of these methods.
 - f. Long-Time- and Short-Time-Delay Functions: Three bands, minimum; marked "minimum," "intermediate," and "maximum."
 - g. Pickup Points: Five minimum, for long-time- and short-time-trip functions. Equip short-time-trip function for switchable I-squared-t operation.
 - h. Pickup Points: Five minimum, for instantaneous-trip functions.
 - i. Ground-fault protection with at least three short-time-delay settings and three trip-time-delay bands; adjustable current pickup. Arrange to provide protection for the following:
 - 1) Three-wire circuit or system.
 - 2) Four-wire circuit or system.
 - 3) Four-wire, double-ended substation.
 - j. Trip Indication: Labeled, battery-powered lights or mechanical targets on trip device to indicate type of fault.
 5. Auxiliary Contacts: For interlocking or remote indication of circuit-breaker position, with spare auxiliary switches and other auxiliary switches required for normal circuit-breaker operation, quantity as indicated. Each consists of two Type "a" and two Type "b" stages (contacts) wired through secondary disconnect devices to a terminal block in stationary housing.
 6. Drawout Features: Circuit-breaker mounting assembly equipped with a racking mechanism to position circuit breaker and hold it rigidly in connected, test, and disconnected positions.

- a. Interlocks: Prevent movement of circuit breaker to or from connected position when it is closed.
- b. Circuit-Breaker Positioning:
 - 1) An open circuit breaker may be racked to or from connected, test, and disconnected positions only with the associated compartment door closed, unless live parts are covered by a full dead-front shield.
 - 2) An open circuit breaker may be manually withdrawn to a position for removal from the structure with the door open.
 - 3) Status for connection devices for different positions includes the following:
 - a) Test Position: Primary disconnect devices disengaged, and secondary disconnect devices and ground contact engaged.
 - b) Disconnected Position: Primary and secondary devices and ground contact disengaged.
- 7. Arc Chutes: Readily removable from associated circuit breaker when it is in disconnected position; arranged to permit inspection of contacts without removing circuit breaker from switchgear.
- 8. Padlocking Provisions: For installing at least three padlocks on each circuit breaker to secure its enclosure and prevent movement of drawout mechanism.
- 9. Operating Handle: One for each circuit breaker capable of manual operation.
 - a. Generator Paralleling Circuit Breakers: Interlocked with system control so that circuit breaker does not close unless mode selector switch is in "Auto" position and engine generator is synchronized with the isolated paralleling bus.
- 10. Electric Close Button: One for each electrically operated circuit breaker.
 - a. Generator Paralleling Circuit Breakers: Interlocked with system control so that circuit breaker does not close unless mode selector switch is in "Auto" position and engine generator is synchronized with the isolated paralleling bus.
- 11. Mechanical Interlocking of Circuit Breakers: Uses a mechanical tripping lever or equivalent design and electrical interlocks.
- 12. Key Interlocks: Arranged so keys are attached at devices indicated. Mountings and hardware are included where future installation of key-interlock devices is indicated.
- 13. Undervoltage Trip Devices: Instantaneous, with adjustable pickup voltage.
- 14. Undervoltage Trip Devices: Adjustable time-delay and pickup voltage.
- 15. Shunt-Trip Devices:
 - a. 24-V dc for generator paralleling circuit breakers and for distribution paralleling switchgear circuit breakers.
 - b. Where indicated.
- 16. Indicating Lights: To indicate circuit breaker is open or closed, for main and bus tie circuit breakers interlocked either with each other or with external devices.

I. Metering:

- 1. Type and Locations:

- a. Isolated Paralleling Bus: **Multifunction digital-metering monitor**; on door of separate metering compartment.
 - b. TBPP Circuit Breakers: **Multifunction digital-metering monitor**; on circuit-breaker door.
- 2. Instrument Transformers:
 - a. Comply with IEEE C57.13.
 - b. Potential Transformers: Secondary-voltage rating of 120 V and NEMA accuracy class of 0.3 with burdens of W, X, and Y.
 - c. Current Transformers:
 - 1) Burden and accuracy class suitable for connected relays, meters, and instruments.
 - 2) Size for the maximum momentary current amperage based on calculation or the momentary rating of the circuit breaker protecting the conductor.
 - 3) Include shorting-type terminal blocks.
- 3. Multifunction Digital-Metering Monitor:
 - a. Microprocessor-based unit suitable for three- or four-wire systems.
 - b. Inputs from sensors or 5-A current-transformer secondaries, and potential terminals rated to 600 V.
 - c. Switch-selectable digital display with the following features:
 - 1) Phase Currents, Each Phase: Plus or minus 1 percent.
 - 2) Phase-to-Phase Voltages, Three Phase: Plus or minus 1 percent.
 - 3) Phase-to-Neutral Voltages, Three Phase: Plus or minus 1 percent.
 - 4) Three-Phase Real Power: Plus or minus 2 percent.
 - 5) Three-Phase Reactive Power: Plus or minus 2 percent.
 - 6) Power Factor: Plus or minus 2 percent.
 - 7) Frequency: Plus or minus 0.5 percent.
 - 8) Integrated Demand, with Demand Interval Selectable from 5 to 60 Minutes: Plus or minus 2 percent.
 - 9) Accumulated energy, in megawatt hours (joules), plus or minus 2 percent; stored values unaffected by power outages for up to 72 hours.
 - d. Communications module suitable for remote monitoring of meter quantities and functions.
 - e. Mounting: Display and control unit that is flush or semi-recessed mounted in instrument compartment door.
- J. Relays: Comply with IEEE C37.90, integrated digital type; with test blocks and plugs.
 - 1. Functions: **<Insert functions>**.
 - 2. Characteristics: **<Insert characteristics>**.
- K. Door-Mounted Control Components: Industrial-type oiltight devices and digital-display indicator lamps.
- L. Control Power Supply:

1. Control power transformer shall supply 120-V ac control circuits from the generator source through secondary disconnect devices.
2. Include a control power transformer for each generator paralleling switchgear circuit breaker connected to the generator side of the circuit breaker.
3. Include a control power transformer for each distribution paralleling switchgear circuit breaker.
4. Dry-type transformers shall be in separate compartments for units larger than 3 kVA, including primary and secondary fuses.
5. Two control power transformers in separate compartments with necessary interlocking relays; each transformer shall be connected to line side of associated main circuit breaker.
 - a. Secondary windings shall be connected through relay(s) to control bus to effect an automatic transfer scheme.
 - b. Secondary windings shall be connected through an internal automatic transfer switch to paralleling switchgear control power bus.
6. Control Power Fuses: Primary and secondary fuses shall provide current-limiting and overload protection.

M. Control Wiring:

1. Factory installed, complete with bundling, lacing, and protection.
2. Provide flexible conductors for No. 8 AWG and smaller, for conductors across hinges and for conductors for interconnections between shipping units.
3. Conductors shall be sized according to NFPA 70 for duty required.

N. Provision for Future Devices: Equip compartments with rails, mounting brackets, supports, necessary appurtenances, and bus connections.

O. Identification: Comply with requirements in Section 260553 "Identification for Electrical Systems" for electrical identification devices and installation.

1. Identify units, devices, controls, and wiring.
2. Mimic Bus: Continuous mimic bus, applied to front of paralleling low-voltage switchgear, arranged in one-line diagram format, using symbols and lettered designations consistent with approved mimic-bus diagram.
 - a. Mimic-bus segments coordinated with devices in paralleling low-voltage switchgear sections to which applied, to produce a concise visual presentation of principal paralleling switchgear components and connections.
 - b. Medium: Painted graphics, as selected by Architect.
 - c. Color: Contrasting with factory-finish background; as selected by Architect from manufacturer's full range.

P. Outdoor Enclosure Fabrication Requirements: Galvanized steel, weatherproof; integral structural-steel base frame with factory-applied asphaltic undercoating.

1. Features for Each Compartment or Group of Compartments:
 - a. Space heater operating at one-half or less of rated voltage, sized to prevent condensation.

- b. Louvers equipped with insect and rodent screen and filter; arranged to permit air circulation while excluding insects, rodents, and exterior dust.
 - c. Hinged front door with locking provisions.
 - d. Interior light with switch.
 - e. Weatherproof ground-fault circuit-interrupter duplex receptacle.
 - f. Power for air conditioning, heaters, lights, and receptacles to be provided from control power transformer.
- Q. Access: Fabricate enclosure with hinged, rear cover panels to allow access to rear interior of paralleling low-voltage switchgear.
- R. Finish: Manufacturer's standard gray finish over a rust-inhibiting primer on phosphatizing-treated metal surfaces.
- S. Accessories:
 - 1. Tools for circuit-breaker and switchgear tests, inspections, maintenance, and operation.
 - 2. Racking handle to manually move circuit breaker between connected and disconnected positions.
 - 3. Portable test set for testing all functions of circuit-breaker, solid-state trip devices without removal from switchgear.
 - 4. Relay and meter test plugs suitable for testing switchgear meters and switchgear class relays.
- T. Circuit-Breaker Removal Apparatus: Portable, floor-supported, roller-base, elevating carriage arranged for moving circuit breakers in and out of compartments.
- U. Spare-Fuse Cabinet: Identified and compartmented steel box or cabinet with lockable door.
- V. Storage for Manual: Rack or holder, near the operating instructions, for a copy of maintenance manual.

2.4 SOURCE QUALITY CONTROL

- A. Verification of Performance: Rate paralleling low-voltage switchgear, with **generators and transfer switches**, according to operation of functions and features specified.
- B. Paralleling low-voltage switchgear, with **generators and transfer switches**, will be considered defective if it does not pass tests and inspections.
- C. Prepare test and inspection reports.

PART 3 - EXECUTION

3.1 EXAMINATION

- A. Examine areas and conditions, with Installer present, where paralleling low-voltage switchgear will be installed for compliance with installation tolerances, required clearances, and other conditions affecting performance of the Work.

- B. Proceed with installation only after unsatisfactory conditions have been corrected.

3.2 INSTALLATION

- A. Comply with applicable portions in NECA 400.
- B. Equipment Mounting:
 - 1. Install paralleling low-voltage switchgear on cast-in-place concrete equipment base(s). Comply with requirements for equipment bases and foundations as specified on the project plans.
- C. Temporary Lifting Provisions: Remove temporary lifting eyes, channels, brackets, and temporary blocking of moving parts from paralleling low-voltage switchgear units and components.

3.3 IDENTIFICATION

- A. Identify field-installed conductors, interconnecting wiring, and components; provide warning signs as specified in Section 260553 "Identification for Electrical Systems."
- B. Diagrams and Instructions:
 - 1. Frame and mount under clear acrylic plastic on front of paralleling low-voltage switchgear.
 - a. Operating Instructions: Printed basic instructions for paralleling low-voltage switchgear, including control and key-interlock sequences and emergency procedures.
 - b. System Power Riser Diagrams: Depict power sources, feeders, distribution components, and major loads.
 - 2. Storage for Maintenance: Include a rack or holder, near the operating instructions, for a copy of maintenance manual.

3.4 CONNECTIONS

- A. Comply with grounding and bonding requirements in Section 260526 "Grounding and Bonding for Electrical Systems."
- B. Comply with wire and cable requirements in Section 260519 "Low-Voltage Electrical Power Conductors and Cables."

3.5 FIELD QUALITY CONTROL

- A. Prepare for acceptance tests as follows:
 - 1. Test insulation resistance for each switchgear bus, component, connecting supply, feeder, and control circuit.
 - 2. Test continuity of each circuit.

3. Inspect paralleling switchgear installation, including wiring, components, connections, and equipment. **Test and adjust components and equipment.**
 4. Verify that electrical control wiring installation complies with manufacturer's submittal by means of point-to-point continuity testing.
 5. Complete installation and startup checks according to manufacturer's written instructions.
- B. Testing Agency: **Owner will engage** a qualified testing agency to perform tests and inspections.
- C. Manufacturer's Field Service: Engage a factory-authorized service representative to test and inspect components, assemblies, and equipment installations, including connections.
- D. Perform the following tests and inspections:
1. Perform each visual and mechanical inspection and electrical test stated in NETA ATS. Certify compliance with test parameters. Perform NETA tests and inspections for each of the following NETA categories:
 - a. AC generators and emergency systems.
 - b. Switchgear.
 - c. Circuit breakers.
 - d. Instrument transformers.
 - e. Metering and instrumentation.
 - f. Ground-fault systems.
 2. Perform NFPA 100 tests for Type 1 essential power systems.
- E. Paralleling low-voltage switchgear will be considered defective if it does not pass tests and inspections.
- F. Prepare test and inspection reports.
- G. Infrared Scanning: After Substantial Completion, but not more than 60 days after Final Acceptance, perform an infrared scan of each switchgear. Remove front and rear panels so joints and connections are accessible to portable scanner.
1. Follow-up Infrared Scanning: Perform an additional follow-up infrared scan of each switchgear 11 months after date of Substantial Completion.
 2. Instrument: Use an infrared scanning device designed to measure temperature or to detect significant deviations from normal values. Provide calibration record for device.
 3. Record of Infrared Scanning: Prepare a certified report that identifies switchgear checked and that describes scanning results. Include notation of deficiencies detected, remedial action taken, and observations after remedial action.
- H. Test sequence of operation step by step for each mode.

3.6 ADJUSTING

- A. Set field-adjustable, electronic circuit-breaker trip characteristics according to results specified in Section 260573 "Overcurrent Protective Device Coordination Study."

- B. Set field-adjustable, electronic circuit-breaker trip characteristics.

3.7 CLEANING

- A. On completion of installation, inspect interior and exterior of paralleling low-voltage switchgear. Vacuum dirt and debris; do not use compressed air to assist in cleaning. Repair damaged finishes.

3.8 PROTECTION

- A. Temporary Heating: Apply temporary heat to paralleling low-voltage switchgear, according to manufacturer's written instructions, throughout periods when paralleling switchgear environment is not controlled for temperature and humidity within manufacturer's stipulated service conditions.

3.9 DEMONSTRATION

- A. **Engage a factory-authorized service representative to train** Owner's maintenance personnel to adjust, operate, and maintain paralleling low-voltage switchgear.

END OF SECTION 262313

SECTION 262413 - SWITCHBOARDS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:
 - 1. Service and distribution switchboards rated 600 V and less.
 - 2. Surge protection devices.
 - 3. Disconnecting and overcurrent protective devices.
 - 4. Instrumentation.
 - 5. Control power.
 - 6. Accessory components and features.
 - 7. Identification.
 - 8. Mimic bus.

1.3 ACTION SUBMITTALS

- A. Product Data: For each switchboard, overcurrent protective device, surge protection device, ground-fault protector, accessory, and component.
 - 1. Include dimensions and manufacturers' technical data on features, performance, electrical characteristics, ratings, accessories, and finishes.
- B. Shop Drawings: For each switchboard and related equipment.
 - 1. Include dimensioned plans, elevations, sections, and details, including required clearances and service space around equipment. Show tabulations of installed devices, equipment features, and ratings.
 - 2. Detail enclosure types for types other than NEMA 250, Type 1.
 - 3. Detail bus configuration, current, and voltage ratings.
 - 4. Detail short-circuit current rating of switchboards and overcurrent protective devices.
 - 5. Include descriptive documentation of optional barriers specified for electrical insulation and isolation.
 - 6. Detail utility company's metering provisions with indication of approval by utility company.
 - 7. Include evidence of NRTL listing for series rating of installed devices.
 - 8. Detail features, characteristics, ratings, and factory settings of individual overcurrent protective devices and auxiliary components.

9. Include time-current coordination curves for each type and rating of overcurrent protective device included in switchboards. Submit on translucent log-log graft paper; include selectable ranges for each type of overcurrent protective device.
 10. Include diagram and details of proposed mimic bus.
 11. Include schematic and wiring diagrams for power, signal, and control wiring.
- C. Samples: Representative portion of mimic bus with specified material and finish, for color selection.

1.4 INFORMATIONAL SUBMITTALS

- A. Qualification Data: For **Installer and testing agency**.
- B. Seismic Qualification Data: Certificates, for switchboards, overcurrent protective devices, accessories, and components, from manufacturer.
1. Basis for Certification: Indicate whether withstand certification is based on actual test of assembled components or on calculation.
 2. Dimensioned Outline Drawings of Equipment Unit: Identify center of gravity and locate and describe mounting and anchorage provisions.
 3. Detailed description of equipment anchorage devices on which the certification is based and their installation requirements.
- C. Field Quality-Control Reports:
1. Test procedures used.
 2. Test results that comply with requirements.
 3. Results of failed tests and corrective action taken to achieve test results that comply with requirements.

1.5 CLOSEOUT SUBMITTALS

- A. Operation and Maintenance Data: For switchboards and components to include in emergency, operation, and maintenance manuals.
1. In addition to items specified in Section 017823 "Operation and Maintenance Data," include the following:
 - a. Routine maintenance requirements for switchboards and all installed components.
 - b. Manufacturer's written instructions for testing and adjusting overcurrent protective devices.
 - c. Time-current coordination curves for each type and rating of overcurrent protective device included in switchboards. Submit on translucent log-log graft paper; include selectable ranges for each type of overcurrent protective device.

1.6 MAINTENANCE MATERIAL SUBMITTALS

- A. Furnish extra materials that match products installed and that are packaged with protective covering for storage and identified with labels describing contents.

1. Potential Transformer Fuses: Equal to 10 percent of quantity installed for each size and type but no fewer than two of each size and type.
2. Control-Power Fuses: Equal to 10 percent of quantity installed for each size and type, but no fewer than two of each size and type.
3. Fuses and Fusible Devices for Fused Circuit Breakers: Equal to 10 percent of quantity installed for each size and type but no fewer than three of each size and type.
4. Fuses for Fused Switches: Equal to 10 percent of quantity installed for each size and type but no fewer than three of each size and type.
5. Fuses for Fused Power-Circuit Devices: Equal to 10 percent of quantity installed for each size and type but no fewer than three of each size and type.
6. Indicating Lights: Equal to 10 percent of quantity installed for each size and type but no less than one of each size and type.

1.7 QUALITY ASSURANCE

- A. Installer Qualifications: An employer of workers qualified as defined in NEMA PB 2.1 and trained in electrical safety as required by NFPA 70E.
- B. Testing Agency Qualifications: Member company of NETA or an NRTL.
 1. Testing Agency's Field Supervisor: Certified by NETA to supervise on-site testing.

1.8 DELIVERY, STORAGE, AND HANDLING

- A. Deliver switchboards in sections or lengths that can be moved past obstructions in delivery path.
- B. Remove loose packing and flammable materials from inside switchboards and **connect factory-installed space heaters to temporary electrical service** to prevent condensation.
- C. Handle and prepare switchboards for installation according to **NEMA PB 2.1**.

1.9 FIELD CONDITIONS

- A. Installation Pathway: Remove and replace access fencing, doors, lift-out panels, and structures to provide pathway for moving switchboards into place.
- B. Environmental Limitations (interior locations):
 1. Do not deliver or install switchboards until spaces are enclosed and weathertight, wet work in spaces is complete and dry, work above switchboards is complete, and **temporary** HVAC system is operating and maintaining ambient temperature and humidity conditions at occupancy levels during the remainder of the construction period.
 2. Rate equipment for continuous operation under the following conditions unless otherwise indicated:
 - a. Ambient Temperature: Not exceeding 104 deg F (40 deg C).
 - b. Altitude: Not exceeding 6600 feet (2000 m).
- C. Unusual Service Conditions - All: NEMA PB 2, as follows:

1. Ambient temperatures within limits specified.
 2. Altitude not exceeding 6600 feet (2000 m).
- D. Interruption of Existing Electric Service: Do not interrupt electric service to facilities occupied by Owner or others unless permitted under the following conditions and then only after arranging to provide temporary electric service according to requirements indicated:
1. Notify **Construction Manager and Owner** no fewer than **seven** days in advance of proposed interruption of electric service.
 2. Indicate method of providing temporary electric service.
 3. Do not proceed with interruption of electric service without **Construction Manager's** and **Owner's** written permission.
 4. Comply with NFPA 70E.

1.10 COORDINATION

- A. Coordinate layout and installation of switchboards and components with other construction that penetrates walls or is supported by them, including electrical and other types of equipment, raceways, piping, encumbrances to workspace clearance requirements, and adjacent surfaces. Maintain required workspace clearances and required clearances for equipment access doors and panels.
- B. Coordinate sizes and locations of concrete bases with actual equipment provided. Cast anchor-bolt inserts into bases. Concrete, reinforcement, and formwork requirements are specified with concrete.

1.11 WARRANTY

- A. Manufacturer's Warranty: Manufacturer agrees to repair or replace switchboard enclosures, buswork, overcurrent protective devices, accessories, and factory installed interconnection wiring that fail in materials or workmanship within specified warranty period.
1. Warranty Period: **Three** years from date of Substantial Completion.
- B. Manufacturer's Warranty: Manufacturer's agrees to repair or replace surge protection devices that fail in materials or workmanship within specified warranty period.
1. Warranty Period: **Five** years from date of Substantial Completion.

PART 2 - PRODUCTS

2.1 PERFORMANCE REQUIREMENTS

- A. Seismic Performance: Switchboards shall withstand the effects of earthquake motions determined according to **ASCE/SEI 7**.

1. Basis for Certification: Indicate whether withstand certification is based on actual test of assembled components or on calculation. Shake-table testing shall comply with ICC-ES AC156.
2. The term "withstand" means "the unit will remain in place without separation of any parts from the device when subjected to the seismic forces specified **and the unit will be fully operational after the seismic event.**"

2.2 SWITCHBOARDS

- A. Source Limitations: Obtain switchboards, overcurrent protective devices, components, and accessories from single source from single manufacturer.
- B. Product Selection for Restricted Space: Drawings indicate maximum dimensions for switchboards including clearances between switchboards and adjacent surfaces and other items. Comply with indicated maximum dimensions.
- C. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and application.
- D. Comply with NEMA PB 2.
- E. Comply with NFPA 70.
- F. Comply with UL 891.
- G. Front-Connected, Front-Accessible Switchboards:
 1. Main Devices: **[Fixed, individually]** mounted.
 2. Branch Devices: Panel mounted.
 3. Sections front and rear aligned.
- H. Front- and Side-Accessible Switchboards:
 1. Main Devices: Fixed, individually mounted.
 2. Branch Devices: Panel mounted.
 3. Section Alignment: **Front** aligned.
- I. Front- and Rear-Accessible Switchboards:
 1. Main Devices: **Fixed, individually** mounted.
 2. Branch Devices: **Panel and fixed, individually** mounted.
 3. Sections **front and rear** aligned.
- J. Nominal System Voltage: Verify service voltage - **480Y/277 V or 208Y/120 V**.
- K. Main-Bus Continuous: **1200 A**.
 1. Aggregation switchboard shall be as noted on the project plans.
- L. Seismic Requirements: Fabricate and test switchboards according to IEEE 344 to withstand seismic forces defined in Section 260548.16 "Seismic Controls for Electrical Systems."

1. Basis for Certification: Indicate whether withstand certification is based on actual test of assembled components or on calculation. Shake-table testing shall comply with ICC-ES AC156.
 - a. The term "withstand" means "the unit will remain in place without separation of any parts from the device when subjected to the seismic forces specified."
 - b. The term "withstand" means "the unit will remain in place without separation of any parts from the device when subjected to the seismic forces specified and the unit will be fully operational after the seismic event."
- M. Indoor Enclosures: Steel, NEMA 250, [Type 1] [Type 2].
- N. Enclosure Finish for Indoor Units: Factory-applied finish in manufacturer's **standard gray** finish over a rust-inhibiting primer on treated metal surface.
- O. Outdoor Enclosures: **Type 3R**.
 1. Finish: Factory-applied finish in manufacturer's **standard** color; undersurfaces treated with corrosion-resistant undercoating.
 2. Enclosure: **Downward, rearward sloping roof; bolt-on rear covers** for each section, with provisions for padlocking.
- P. Barriers: Between adjacent switchboard sections.
- Q. Insulation and isolation for [**main bus of main section and**] main and vertical buses of feeder sections.
- R. Space Heaters: Factory-installed electric space heaters of sufficient wattage in each vertical section to maintain enclosure temperature above expected dew point.
 1. Space-Heater Control: [**Thermostats to maintain temperature of each section above expected dew point**] [Manual switching of branch-circuit protective device].
 2. Space-Heater Power Source: [**Transformer, factory installed in switchboard**] [120-V external branch circuit].
- S. Customer Metering Compartment: A separate customer metering compartment and section with front hinged door, for indicated metering, and current transformers for each meter. Current transformer secondary wiring shall be terminated on shorting-type terminal blocks. **Include potential transformers having primary and secondary fuses with disconnecting means and secondary wiring terminated on terminal blocks.**
- T. Bus Transition and Incoming Pull Sections: Matched and aligned with basic switchboard.
- U. Removable, Hinged Rear Doors and Compartment Covers: Secured by **standard bolts**, for access to rear interior of switchboard.
- V. Hinged Front Panels: Allow access to circuit breaker, metering, accessory, and blank compartments.
- W. Pull Box on Top of Switchboard:

1. Adequate ventilation to maintain temperature in pull box within same limits as switchboard.
2. Set back from front to clear circuit-breaker removal mechanism.
3. Removable covers shall form top, front, and sides. Top covers at rear shall be easily removable for drilling and cutting.
4. Bottom shall be insulating, fire-resistive material with separate holes for cable drops into switchboard.
5. Cable supports shall be arranged to facilitate cabling and adequate to support cables indicated, including those for future installation.

X. Buses and Connections: Three phase, four wire unless otherwise indicated.

1. Provide phase bus arrangement A, B, C from front to back, top to bottom, and left to right when viewed from the front of the switchboard.
2. Phase- and Neutral-Bus Material: Hard-drawn copper of 98 percent conductivity, **silver-plated**.
3. Phase- and Neutral-Bus Material: Tin-plated, high-strength, electrical-grade aluminum alloy with tin-plated aluminum circuit-breaker line connections.
4. Copper feeder circuit-breaker line connections.
5. Tin-plated aluminum feeder circuit-breaker line connections.
6. Load Terminals: Insulated, rigidly braced, runback bus extensions, of same material as through buses, equipped with **[mechanical] [compression]** connectors for outgoing circuit conductors. Provide load terminals for future circuit-breaker positions at full-ampere rating of circuit-breaker position.
7. Ground Bus: **Minimum-size required by UL 891**, hard-drawn copper of 98 percent conductivity, equipped with **mechanical** connectors for feeder and branch-circuit ground conductors.
8. Main-Phase Buses and Equipment-Ground Buses: Uniform capacity for entire length of switchboard's main and distribution sections. Provide for future extensions from both ends.
9. Disconnect Links:
 - a. Isolate neutral bus from incoming neutral conductors.
 - b. Bond neutral bus to equipment-ground bus for switchboards utilized as service equipment or separately derived systems.
10. Neutral Buses: 50 percent of the ampacity of phase buses unless otherwise indicated, equipped with **mechanical** connectors for outgoing circuit neutral cables. Brace bus extensions for busway feeder neutral bus.
11. Neutral Buses: 100 percent of the ampacity of phase buses unless otherwise indicated, equipped with **mechanical** connectors for outgoing circuit neutral cables. Brace bus extensions for busway feeder neutral bus.
12. Isolation Barrier Access Provisions: Permit checking of bus-bolt tightness.

Y. Future Devices: Equip compartments with mounting brackets, supports, bus connections, and appurtenances at full rating of circuit-breaker compartment.

Z. Bus-Bar Insulation: Factory-applied, flame-retardant, tape wrapping of individual bus bars or flame-retardant, spray-applied insulation. Minimum insulation temperature rating of 105 deg C.

AA. Fungus Proofing: Permanent fungicidal treatment for overcurrent protective devices and other components including instruments and instrument transformers.

2.3 SURGE PROTECTION DEVICES

- A. SPDs: Comply with UL 1449, [Type 1] [Type 2].
- B. SPDs: Listed and labeled by an NRTL acceptable to authorities having jurisdiction as complying with UL 1449, Type 1.
- C. Features and Accessories:
 - 1. Integral disconnect switch.
 - 2. Internal thermal protection that disconnects the SPD before damaging internal suppressor components.
 - 3. Indicator light display for protection status.
 - 4. Form-C contacts rated at **5 A and 250-V ac**, one normally open and one normally closed, for remote monitoring of protection status.
 - 5. Surge counter.
- D. Peak Surge Current Rating: The minimum single-pulse surge current withstand rating per phase shall not be less than **300 kA**. The peak surge current rating shall be the arithmetic sum of the ratings of the individual MOVs in a given mode.
- E. Protection modes and UL 1449 VPR for grounded wye circuits with **480Y/277 V or 208Y/120 V**, three-phase, four-wire circuits shall not exceed the following:
 - 1. Line to Neutral: **1200 V for 480Y/277 V or 700 V for 208Y/120 V**.
 - 2. Line to Ground: **1200 V for 480Y/277 V or 1200 V for 208Y/120 V**.
 - 3. Line to Line: **2000 V for 480Y/277 V or 1000 V for 208Y/120 V**.
- F. Protection modes and UL 1449 VPR for 240/120 V, single-phase, three-wire circuits shall not exceed the following:
 - 1. Line to Neutral: 700 V.
 - 2. Line to Ground: **700 V**.
 - 3. Line to Line: 1000 V.
- G. SCCR: Equal or exceed **100 kA**.
- H. Nominal Rating: 20 kA.

2.4 DISCONNECTING AND OVERCURRENT PROTECTIVE DEVICES

- A. Molded-Case Circuit Breaker (MCCB): Comply with UL 489, with **interrupting capacity** to meet available fault currents.
 - 1. Thermal-Magnetic Circuit Breakers: Inverse time-current element for low-level overloads and instantaneous magnetic trip element for short circuits. Adjustable magnetic trip setting for circuit-breaker frame sizes 250 A and larger.
 - 2. Electronic trip circuit breakers with rms sensing; field-replaceable rating plug or field-replaceable electronic trip; and the following field-adjustable settings:
 - a. Instantaneous trip.

- b. Long- and short-time pickup levels.
 - c. Long and short time adjustments.
 - d. Ground-fault pickup level, time delay, and I^2t response.
3. MCCB Features and Accessories:
- a. Standard frame sizes, trip ratings, and number of poles.
 - b. Lugs: **Mechanical** style, suitable for number, size, trip ratings, and conductor material.
 - c. Application Listing: Appropriate for application; Type SWD for switching fluorescent lighting loads; Type HID for feeding fluorescent and high-intensity discharge (HID) lighting circuits.
 - d. Ground-Fault Protection: **Integrally mounted** relay and trip unit with adjustable pickup and time-delay settings, push-to-test feature, and ground-fault indicator.
 - e. Zone-Selective Interlocking: Integral with electronic trip unit; for interlocking ground-fault protection function.
 - f. Communication Capability: **Circuit-breaker-mounted** communication module with functions and features compatible with power monitoring and control system specified in Section 260913 "Electrical Power Monitoring and Control."
 - g. Shunt Trip: 120-V trip coil energized from separate circuit, set to trip at 55 percent of rated voltage.
 - h. Undervoltage Trip: Set to operate at 35 to 75 percent of rated voltage without intentional time delay.
 - i. Auxiliary Contacts: **One SPDT switch** with "a" and "b" contacts; "a" contacts mimic circuit-breaker contacts, "b" contacts operate in reverse of circuit-breaker contacts.

2.5 INSTRUMENTATION

A. Instrument Transformers: NEMA EI 21.1, and the following:

- 1. Potential Transformers: NEMA EI 21.1; 120 V, 60 Hz, **single** secondary; disconnecting type with integral fuse mountings. Burden and accuracy shall be consistent with connected metering and relay devices.
- 2. Current Transformers: NEMA EI 21.1; 5 A, 60 Hz, secondary; **bar or window** type; **single** secondary winding and secondary shorting device. Burden and accuracy shall be consistent with connected metering and relay devices.
- 3. Control-Power Transformers: Dry type, mounted in separate compartments for units larger than 3 kVA.
- 4. Current Transformers for Neutral and Ground-Fault Current Sensing: Connect secondary wiring to ground overcurrent relays, via shorting terminals, to provide selective tripping of main and tie circuit breaker. Coordinate with feeder circuit-breaker, ground-fault protection.

B. Multifunction Digital-Metering Monitor: Microprocessor-based unit suitable for three- or four-wire systems and with the following features:

- 1. Switch-selectable digital display of the following values with maximum accuracy tolerances as indicated:
 - a. Phase Currents, Each Phase: Plus or minus 0.5 percent.

- b. Phase-to-Phase Voltages, Three Phase: Plus or minus 0.5 percent.
 - c. Phase-to-Neutral Voltages, Three Phase: Plus or minus 0.5 percent.
 - d. Megawatts: Plus or minus 1 percent.
 - e. Megavars: Plus or minus 1 percent.
 - f. Power Factor: Plus or minus 1 percent.
 - g. Frequency: Plus or minus 0.1 percent.
 - h. Accumulated Energy, Megawatt Hours: Plus or minus 1 percent; accumulated values unaffected by power outages up to 72 hours.
 - i. Megawatt Demand: Plus or minus 1 percent; demand interval programmable from five to 60 minutes.
 - j. Contact devices to operate remote impulse-totalizing demand meter.
- 2. Mounting: Display and control unit flush or semiflush mounted in instrument compartment door.
- C. Analog Meters:
 - 1. Meters: 4-inch (100-mm) diameter or 6 inches (150 mm) square, flush or semiflush, with anti-parallax 250-degree scales and external zero adjustment.
- D. Voltmeters: Cover an expanded-scale range of nominal voltage plus 10 percent.
- E. Instrument Switches: Rotary type with off position.
 - 1. Voltmeter Switches: Permit reading of all phase-to-phase voltages and, where a neutral is indicated, phase-to-neutral voltages.
 - 2. Ammeter Switches: Permit reading of current in each phase and maintain current-transformer secondaries in a closed-circuit condition at all times.
- F. Ammeters: 2-1/2-inch (64-mm) minimum size with 90- or 120-degree scale. Meter and transfer device with off position, located on overcurrent device door for indicated feeder circuits only.
- G. Watt-Hour Meters and Wattmeters:
 - 1. Comply with ANSI C12.1.
 - 2. Three-phase induction type with two stators, each with current and potential coil, rated 5 A, 120 V, 60 Hz.
 - 3. Suitable for connection to three- and four-wire circuits.
 - 4. Potential indicating lamps.
 - 5. Adjustments for light and full load, phase balance, and power factor.
 - 6. Four-dial clock register.
 - 7. Integral demand indicator.
 - 8. Contact devices to operate remote impulse-totalizing demand meter.
 - 9. Ratchets to prevent reverse rotation.
 - 10. Removable meter with drawout test plug.
 - 11. Semiflush mounted case with matching cover.
 - 12. Appropriate multiplier tag.
- H. Impulse-Totalizing Demand Meter:
 - 1. Comply with ANSI C12.1.

2. Suitable for use with switchboard watt-hour meter, including two-circuit totalizing relay.
3. Cyclometer.
4. Four-dial, totalizing kilowatt-hour register.
5. Positive chart drive mechanism.
6. Capillary pen holding a minimum of one month's ink supply.
7. Roll chart with minimum 31-day capacity; appropriate multiplier tag.
8. Capable of indicating and recording [five] [15] [30] <Insert time period>-minute integrated demand of totalized system.

2.6 CONTROL POWER

- A. Control Circuits: 120-V ac, supplied through secondary disconnecting devices from control-power transformer.
- B. Control Circuits: 120-V ac, supplied from remote branch circuit.
- C. Control-Power Fuses: Primary and secondary fuses for current-limiting and overload protection of transformer and fuses for protection of control circuits.
- D. Control Wiring: Factory installed, with bundling, lacing, and protection included. Provide flexible conductors for No. 8 AWG and smaller, for conductors across hinges, and for conductors for interconnections between shipping units.

2.7 ACCESSORY COMPONENTS AND FEATURES

- A. Accessory Set: Include tools and miscellaneous items required for overcurrent protective device test, inspection, maintenance, and operation.
- B. Portable Test Set: For testing functions of solid-state trip devices without removing from switchboard. Include relay and meter test plugs suitable for testing switchboard meters and switchboard class relays.
- C. Portable Circuit-Breaker Lifting Device: Floor-supported, roller-based, elevating carriage arranged for movement of circuit breakers in and out of compartments for present and future circuit breakers.
- D. Overhead Circuit-Breaker Lifting Device: Mounted at top front of switchboard, with hoist and lifting yokes matching each drawout circuit breaker.
- E. Spare-Fuse Cabinet: Suitably identified, wall-mounted, lockable, compartmented steel box or cabinet. Arrange for wall mounting.
- F. Mounting Accessories: For anchors, mounting channels, bolts, washers, and other mounting accessories, comply with requirements in Section 260548.16 "Seismic Controls for Electrical Systems" or manufacturer's instructions.

2.8 IDENTIFICATION

- A. Mimic Bus: Entire single-line switchboard bus work, as depicted on factory record drawing, on a photoengraved nameplate.
 - 1. Nameplate: At least 0.032-inch- (0.813-mm-) thick anodized aluminum, located at eye level on front cover of the switchboard incoming service section.
- B. Mimic Bus: Entire single-line switchboard bus work, as depicted on factory record drawing, on an engraved laminated-plastic (Gravoply) nameplate.
 - 1. Nameplate: At least 0.0625-inch- (1.588 mm-) thick laminated plastic (Gravoply), located at eye level on front cover of the switchboard incoming service section.
- C. Mimic Bus: Continuously integrated mimic bus factory applied to front of switchboard. Arrange in single-line diagram format, using symbols and letter designations consistent with final mimic-bus diagram.
- D. Coordinate mimic-bus segments with devices in switchboard sections to which they are applied. Produce a concise visual presentation of principal switchboard components and connections.
- E. Presentation Media: Painted graphics in color contrasting with background color to represent bus and components, complete with lettered designations.
- F. Service Equipment Label: NRTL labeled for use as service equipment for switchboards with one or more service disconnecting and overcurrent protective devices.

PART 3 - EXECUTION

3.1 EXAMINATION

- A. Receive, inspect, handle, and store switchboards according to **NEMA PB 2.1**.
 - 1. Lift or move panelboards with spreader bars and manufacturer-supplied lifting straps following manufacturer's instructions.
 - 2. Use rollers, slings, or other manufacturer-approved methods if lifting straps are not furnished.
 - 3. Protect from moisture, dust, dirt, and debris during storage and installation.
 - 4. Install temporary heating during storage per manufacturer's instructions.
- B. Examine switchboards before installation. Reject switchboards that are moisture damaged or physically damaged.
- C. Examine elements and surfaces to receive switchboards for compliance with installation tolerances and other conditions affecting performance of the Work or that affect the performance of the equipment.
- D. Proceed with installation only after unsatisfactory conditions have been corrected.

3.2 INSTALLATION

- A. Install switchboards and accessories according to **NEMA PB 2.1**.
- B. Equipment Mounting: Install switchboards on concrete base, 4-inch (100-mm) nominal thickness. Comply with requirements for concrete base specified on project plans.
 - 1. Install conduits entering underneath the switchboard, entering under the vertical section where the conductors will terminate. Install with couplings flush with the concrete base. Extend 2 inches (50-mm) above concrete base after switchboard is anchored in place.
 - 2. Install dowel rods to connect concrete base to concrete floor. Unless otherwise indicated, install dowel rods on 18-inch (450-mm) centers around the full perimeter of concrete base.
 - 3. For supported equipment, install epoxy-coated anchor bolts that extend through concrete base and anchor into structural concrete floor.
 - 4. Place and secure anchorage devices. Use setting drawings, templates, diagrams, instructions, and directions furnished with items to be embedded.
 - 5. Install anchor bolts to elevations required for proper attachment to switchboards.
 - 6. Anchor switchboard to building structure at the top of the switchboard if required or recommended by the manufacturer.
- C. Temporary Lifting Provisions: Remove temporary lifting eyes, channels, straps and brackets, and temporary blocking of moving parts from switchboard units and components.
- D. Operating Instructions: Frame and mount the printed basic operating instructions for switchboards, including control and key interlocking sequences and emergency procedures. Fabricate frame of finished wood or metal and cover instructions with clear acrylic plastic. Mount on front of switchboards.
- E. Install filler plates in unused spaces of panel-mounted sections.
- F. Install overcurrent protective devices, surge protection devices, and instrumentation.
 - 1. Set field-adjustable switches and circuit-breaker trip ranges.
- G. Install spare-fuse cabinet.
- H. Comply with NECA 1.

3.3 CONNECTIONS

- A. Comply with requirements for terminating feeder bus specified in Section 262500 "Enclosed Bus Assemblies." Drawings indicate general arrangement of bus, fittings, and specialties.
- B. Comply with requirements for terminating cable trays specified in Section 260536 "Cable Trays for Electrical Systems." Drawings indicate general arrangement of cable trays, fittings, and specialties.
- C. Bond conduits entering underneath the switchboard to the equipment ground bus with a bonding conductor sized per NFPA 70.
- D. Support and secure conductors within the switchboard according to NFPA 70.

- E. Extend insulated equipment grounding cable to busway ground connection and support cable at intervals in vertical run.

3.4 IDENTIFICATION

- A. Identify field-installed conductors, interconnecting wiring, and components; provide warning signs complying with requirements for identification specified in Section 260553 "Identification for Electrical Systems."
- B. Switchboard Nameplates: Label each switchboard compartment with a nameplate complying with requirements for identification specified in Section 260553 "Identification for Electrical Systems."
- C. Device Nameplates: Label each disconnecting and overcurrent protective device and each meter and control device mounted in compartment doors with a nameplate complying with requirements for identification specified in Section 260553 "Identification for Electrical Systems."

3.5 FIELD QUALITY CONTROL

- A. Testing Agency: **Engage** a qualified testing agency to perform tests and inspections.
- B. Manufacturer's Field Service: Engage a factory-authorized service representative to inspect, test, and adjust components, assemblies, and equipment installations, including connections.
- C. Perform the following tests and inspections **with the assistance of a factory-authorized service representative**:
 - 1. Acceptance Testing:
 - a. Test insulation resistance for each switchboard bus, component, connecting supply, feeder, and control circuit. Open control and metering circuits within the switchboard, and remove neutral connection to surge protection and other electronic devices prior to insulation test. Reconnect after test.
 - b. Test continuity of each circuit.
 - 2. Test ground-fault protection of equipment for service equipment per NFPA 70.
 - 3. Perform each visual and mechanical inspection and electrical test stated in NETA Acceptance Testing Specification. Certify compliance with test parameters.
 - 4. Correct malfunctioning units on-site where possible, and retest to demonstrate compliance; otherwise, replace with new units and retest.
 - 5. Perform the following infrared scan tests and inspections, and prepare reports:
 - a. Initial Infrared Scanning: After Substantial Completion, but not more than 60 days after Final Acceptance, perform an infrared scan of each switchboard. Remove **front and rear** panels so joints and connections are accessible to portable scanner.
 - b. Follow-up Infrared Scanning: Perform an additional follow-up infrared scan of each switchboard 11 months after date of Substantial Completion.
 - c. Instruments and Equipment:

- 1) Use an infrared scanning device designed to measure temperature or to detect significant deviations from normal values. Provide calibration record for device.
6. Test and adjust controls, remote monitoring, and safeties. Replace damaged and malfunctioning controls and equipment.
- D. Switchboard will be considered defective if it does not pass tests and inspections.
- E. Prepare test and inspection reports, including a certified report that identifies switchboards included and that describes scanning results. Include notation of deficiencies detected, remedial action taken, and observations after remedial action.

3.6 ADJUSTING

- A. Adjust moving parts and operable components to function smoothly, and lubricate as recommended by manufacturer.
- B. Set field-adjustable circuit-breaker trip ranges **as indicated**.

3.7 PROTECTION

- A. Temporary Heating: Apply temporary heat, to maintain temperature according to manufacturer's written instructions, until switchboard is ready to be energized and placed into service.

3.8 DEMONSTRATION

- A. **[Engage a factory-authorized service representative to train] [Train] Owner's maintenance personnel to adjust, operate, and maintain switchboards, overcurrent protective devices, instrumentation, and accessories[, and to use and reprogram microprocessor-based trip, monitoring, and communication units].**

END OF SECTION 262413

SECTION 262416 - PANELBOARDS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:
 - 1. Distribution panelboards.
 - 2. Load centers.

1.3 DEFINITIONS

- A. ATS: Acceptance testing specification.
- B. GFCI: Ground-fault circuit interrupter.
- C. GFEP: Ground-fault equipment protection.
- D. HID: High-intensity discharge.
- E. MCCB: Molded-case circuit breaker.
- F. SPD: Surge protective device.
- G. VPR: Voltage protection rating.

1.4 ACTION SUBMITTALS

- A. Product Data: For each type of panelboard.
 - 1. Include materials, switching and overcurrent protective devices, SPDs, accessories, and components indicated.
 - 2. Include dimensions and manufacturers' technical data on features, performance, electrical characteristics, ratings, and finishes.
- B. Shop Drawings: For each panelboard and related equipment.
 - 1. Include dimensioned plans, elevations, sections, and details.
 - 2. Show tabulations of installed devices with nameplates, conductor termination sizes, equipment features, and ratings.

3. Detail enclosure types including mounting and anchorage, environmental protection, knockouts, corner treatments, covers and doors, gaskets, hinges, and locks.
4. Detail bus configuration, current, and voltage ratings.
5. Short-circuit current rating of panelboards and overcurrent protective devices.
6. Include evidence of NRTL listing for series rating of installed devices.
7. Include evidence of NRTL listing for SPD as installed in panelboard.
8. Detail features, characteristics, ratings, and factory settings of individual overcurrent protective devices and auxiliary components.
9. Include wiring diagrams for power, signal, and control wiring.

1.5 INFORMATIONAL SUBMITTALS

- A. Qualification Data: For testing agency.
- B. Panelboard Schedules: For installation in panelboards. **Submit final versions after load balancing.**

1.6 CLOSEOUT SUBMITTALS

- A. Operation and Maintenance Data: For panelboards and components to include in emergency, operation, and maintenance manuals. In addition to items specified in Section 017823 "Operation and Maintenance Data," include the following:
 1. Manufacturer's written instructions for testing and adjusting overcurrent protective devices.
 2. Time-current curves, including selectable ranges for each type of overcurrent protective device that allows adjustments.

1.7 MAINTENANCE MATERIAL SUBMITTALS

- A. Furnish extra materials that match products installed and that are packaged with protective covering for storage and identified with labels describing contents.
 1. Keys: **Two** spares for each type of panelboard cabinet lock.
 2. Circuit Breakers Including GFCI and GFEP Types: **Two** spares for each panelboard.

1.8 QUALITY ASSURANCE

- A. Manufacturer Qualifications: ISO 9001 or 9002 certified.

1.9 DELIVERY, STORAGE, AND HANDLING

- A. Remove loose packing and flammable materials from inside panelboards; install temporary electric heating (250 W per panelboard) to prevent condensation.
- B. Handle and prepare panelboards for installation according to **NEMA PB 1**.

1.10 FIELD CONDITIONS

A. Environmental Limitations (Interior locations):

1. Do not deliver or install panelboards until spaces are enclosed and weathertight, wet work in spaces is complete and dry, work above panelboards is complete, and temporary HVAC system is operating and maintaining ambient temperature and humidity conditions at occupancy levels during the remainder of the construction period.
2. Rate equipment for continuous operation under the following conditions unless otherwise indicated:
 - a. Ambient Temperature: Not exceeding **minus 22 deg F (minus 30 deg C)** to plus 104 deg F (plus 40 deg C).
 - b. Altitude: Not exceeding 6600 feet (2000 m).

B. Service Conditions: NEMA PB 1, usual service conditions, as follows:

1. Ambient temperatures within limits specified.
2. Altitude not exceeding 6600 feet (2000 m).

C. Interruption of Existing Electric Service: Do not interrupt electric service to facilities occupied by Owner or others unless permitted under the following conditions and then only after arranging to provide temporary electric service according to requirements indicated:

1. Notify **Construction Manager and Owner** no fewer than **two** days in advance of proposed interruption of electric service.
2. Do not proceed with interruption of electric service without **Construction Manager's and Owner's** written permission.
3. Comply with NFPA 70E.

1.11 WARRANTY

A. Manufacturer's Warranty: Manufacturer agrees to repair or replace panelboards that fail in materials or workmanship within specified warranty period.

1. Panelboard Warranty Period: **18** months from date of Substantial Completion.

B. Special Warranty: Manufacturer's standard form in which manufacturer agrees to repair or replace SPD that fails in materials or workmanship within specified warranty period.

1. SPD Warranty Period: **Five** years from date of Substantial Completion.

PART 2 - PRODUCTS

2.1 PANELBOARDS AND LOAD CENTERS COMMON REQUIREMENTS

A. Fabricate and test panelboards according to IEEE 344 to withstand seismic forces defined in Section 260548.16 "Seismic Controls for Electrical Systems."

- B. Product Selection for Restricted Space: Drawings indicate maximum dimensions for panelboards including clearances between panelboards and adjacent surfaces and other items. Comply with indicated maximum dimensions.
- C. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and application.
- D. Comply with NEMA PB 1.
- E. Comply with NFPA 70.
- F. Enclosures: **Surface-mounted**, dead-front cabinets.
 - 1. Rated for environmental conditions at installed location.
 - a. Outdoor Locations: **NEMA 250, Type 3R**.
 - 2. Height: 84 inches (2.13 m) maximum.
 - 3. Front: Secured to box with concealed trim clamps. For surface-mounted fronts, match box dimensions; for flush-mounted fronts, overlap box. Trims shall cover all live parts and shall have no exposed hardware.
 - 4. Hinged Front Cover: Entire front trim hinged to box and with standard door within hinged trim cover. Trims shall cover all live parts and shall have no exposed hardware.
 - 5. Skirt for Surface-Mounted Panelboards: Same gage and finish as panelboard front with flanges for attachment to panelboard, wall, and ceiling or floor.
 - 6. Gutter Extension and Barrier: Same gage and finish as panelboard enclosure; integral with enclosure body. Arrange to isolate individual panel sections.
 - 7. Finishes:
 - a. Panels and Trim: **Steel and galvanized steel**, factory finished immediately after cleaning and pretreating with manufacturer's standard two-coat, baked-on finish consisting of prime coat and thermosetting topcoat.
 - b. Back Boxes: **Galvanized steel**.
 - c. Fungus Proofing: Permanent fungicidal treatment for overcurrent protective devices and other components.
- G. Incoming Mains:
 - 1. Location: **Convertible between top and bottom**.
 - 2. Main Breaker: Main lug interiors up to 400 amperes shall be field convertible to main breaker.
- H. Phase, Neutral, and Ground Buses:
 - 1. Material: **Tin-plated aluminum**.
 - a. Plating shall run entire length of bus.
 - b. Bus shall be fully rated the entire length.
 - 2. Interiors shall be factory assembled into a unit. Replacing switching and protective devices shall not disturb adjacent units or require removing the main bus connectors.

3. Equipment Ground Bus: Adequate for feeder and branch-circuit equipment grounding conductors; bonded to box.
4. Full-Sized Neutral: Equipped with full-capacity bonding strap for service entrance applications. Mount electrically isolated from enclosure. Do not mount neutral bus in gutter.

I. Conductor Connectors: Suitable for use with conductor material and sizes.

1. Material: **Hard-drawn copper, 98 percent conductivity.**
2. Terminations shall allow use of 75 deg C rated conductors without derating.
3. Size: Lugs suitable for indicated conductor sizes, with additional gutter space, if required, for larger conductors.
4. Main and Neutral Lugs: **Mechanical** type, with a lug on the neutral bar for each pole in the panelboard.
5. Ground Lugs and Bus-Configured Terminators: **Mechanical** type, with a lug on the bar for each pole in the panelboard.
6. Feed-Through Lugs: **Mechanical** type, suitable for use with conductor material. Locate at opposite end of bus from incoming lugs or main device.
7. Subfeed (Double) Lugs: **Mechanical** type suitable for use with conductor material. Locate at same end of bus as incoming lugs or main device.
8. Gutter-Tap Lugs: **Mechanical** type suitable for use with conductor material and with matching insulating covers. Locate at same end of bus as incoming lugs or main device.
9. Extra-Capacity Neutral Lugs: Rated 200 percent of phase lugs mounted on extra-capacity neutral bus.

J. NRTL Label: Panelboards or load centers shall be labeled by an NRTL acceptable to authority having jurisdiction for use as service equipment with one or more main service disconnecting and overcurrent protective devices. Panelboards or load centers shall have meter enclosures, wiring, connections, and other provisions for utility metering. Coordinate with utility company for exact requirements.

K. Future Devices: Panelboards or load centers shall have mounting brackets, bus connections, filler plates, and necessary appurtenances required for future installation of devices.

1. Percentage of Future Space Capacity: **Five percent.**

L. Panelboard Short-Circuit Current Rating: Fully rated to interrupt symmetrical short-circuit current available at terminals. Assembly listed by an NRTL for 100 percent interrupting capacity.

1. Panelboards and overcurrent protective devices rated 240 V or less shall have short-circuit ratings as shown on Drawings, but not less than 10,000 A rms symmetrical.
2. Panelboards and overcurrent protective devices rated above 240 V and less than 600 V shall have short-circuit ratings as shown on Drawings, but not less than 14,000 A rms symmetrical.

2.2 PERFORMANCE REQUIREMENTS

A. Seismic Performance: Panelboards shall withstand the effects of earthquake motions determined according to **ASCE/SEI 7**.

1. The term "withstand" means "the unit will remain in place without separation of any parts from the device when subjected to the seismic forces specified."
- B. Surge Suppression: Factory installed as an integral part of indicated panelboards, complying with UL 1449 SPD Type 1.

2.3 POWER PANELBOARDS

- A. Panelboards: NEMA PB 1, distribution type.
- B. Doors: Secured with vault-type latch with tumbler lock; keyed alike.
 1. For doors more than **36 inches (914 mm)** high, provide two latches, keyed alike.
- C. Mains: **Circuit breaker.**
- D. Branch Overcurrent Protective Devices for Circuit-Breaker Frame Sizes 125 A and Smaller: **Bolt-on circuit breakers.**
- E. Branch Overcurrent Protective Devices for Circuit-Breaker Frame Sizes Larger Than 125 A: **Bolt-on circuit breakers.**

2.4 LOAD CENTERS

- A. Load Centers: Comply with UL 67.
- B. Mains: **Circuit breaker.**
- C. Branch Overcurrent Protective Devices: Plug-in circuit breakers, replaceable without disturbing adjacent units.
- D. Doors: Concealed hinges secured with flush latch with tumbler lock; keyed alike.
- E. Conductor Connectors: Mechanical type for main, neutral, and ground lugs and buses.

2.5 DISCONNECTING AND OVERCURRENT PROTECTIVE DEVICES

- A. MCCB: Comply with UL 489, with **interrupting capacity** to meet available fault currents.
 1. Thermal-Magnetic Circuit Breakers:
 - a. Inverse time-current element for low-level overloads.
 - b. Instantaneous magnetic trip element for short circuits.
 - c. Adjustable magnetic trip setting for circuit-breaker frame sizes 250 A and larger.

2.6 IDENTIFICATION

- A. Panelboard Label: Manufacturer's name and trademark, voltage, amperage, number of phases, and number of poles shall be located on the interior of the panelboard door.
- B. Breaker Labels: Faceplate shall list current rating, UL and IEC certification standards, and AIC rating.
- C. Circuit Directory: Directory card inside panelboard door, mounted in **metal frame with transparent protective cover**.
 - 1. Circuit directory shall identify specific purpose with detail sufficient to distinguish it from all other circuits.

2.7 ACCESSORY COMPONENTS AND FEATURES

- A. Accessory Set: Include tools and miscellaneous items required for overcurrent protective device test, inspection, maintenance, and operation.
- B. Portable Test Set: For testing functions of solid-state trip devices without removing from panelboard. Include relay and meter test plugs suitable for testing panelboard meters and switchboard class relays.

PART 3 - EXECUTION

3.1 EXAMINATION

- A. Verify actual conditions with field measurements prior to ordering panelboards to verify that equipment fits in allocated space in, and comply with, minimum required clearances specified in NFPA 70.
- B. Receive, inspect, handle, and store panelboards according to **NEMA PB 1.1**.
- C. Examine panelboards before installation. Reject panelboards that are damaged, rusted, or have been subjected to water saturation.
- D. Examine elements and surfaces to receive panelboards for compliance with installation tolerances and other conditions affecting performance of the Work.
- E. Proceed with installation only after unsatisfactory conditions have been corrected.

3.2 INSTALLATION

- A. Coordinate layout and installation of panelboards and components with other construction that penetrates walls or is supported by them, including electrical and other types of equipment, raceways, piping, encumbrances to workspace clearance requirements, and adjacent surfaces. Maintain required workspace clearances and required clearances for equipment access doors and panels.

- B. Comply with NECA 1.
- C. Install panelboards and accessories according to [NECA 407] [NEMA PB 1.1].
- D. Equipment Mounting:
 - 1. Attach panelboard to the vertical finished or structural surface behind the panelboard.
- E. Temporary Lifting Provisions: Remove temporary lifting eyes, channels, and brackets and temporary blocking of moving parts from panelboards.
- F. Comply with mounting and anchoring requirements specified in Section 260548.16 "Seismic Controls for Electrical Systems."
- G. Mount top of trim **90 inches (2286 mm)** above finished floor unless otherwise indicated.
- H. Mount panelboard cabinet plumb and rigid without distortion of box.
- I. Mount recessed panelboards with fronts uniformly flush with wall finish and mating with back box.
- J. Mount surface-mounted panelboards to steel slotted supports **5/8 inch (16 mm)** in depth. Orient steel slotted supports vertically.
- K. Install overcurrent protective devices and controllers not already factory installed.
 - 1. Set field-adjustable, circuit-breaker trip ranges.
 - 2. Tighten bolted connections and circuit breaker connections using calibrated torque wrench or torque screwdriver per manufacturer's written instructions.
- L. Make grounding connections and bond neutral for services and separately derived systems to ground. Make connections to grounding electrodes, separate grounds for isolated ground bars, and connections to separate ground bars.
- M. Install filler plates in unused spaces.
- N. Arrange conductors in gutters into groups and bundle and wrap with wire ties **after completing load balancing**.

3.3 IDENTIFICATION

- A. Identify field-installed conductors, interconnecting wiring, and components; install warning signs complying with requirements in Section 260553 "Identification for Electrical Systems."
- B. Create a directory to indicate installed circuit loads **after balancing panelboard loads**; incorporate Owner's final areas designations. Obtain approval before installing. Handwritten directories are not acceptable. Install directory inside panelboard door.
- C. Panelboard Nameplates: Label each panelboard with a nameplate complying with requirements for identification specified in Section 260553 "Identification for Electrical Systems."

- D. Device Nameplates: Label each branch circuit device in power panelboards with a nameplate complying with requirements for identification specified in Section 260553 "Identification for Electrical Systems."
- E. Install warning signs complying with requirements in Section 260553 "Identification for Electrical Systems" identifying source of remote circuit.

3.4 FIELD QUALITY CONTROL

- A. Manufacturer's Field Service: Engage a factory-authorized service representative to inspect, test, and adjust components, assemblies, and equipment installations, including connections.
- B. Perform tests and inspections.
 - 1. Manufacturer's Field Service: Engage a factory-authorized service representative to inspect components, assemblies, and equipment installations, including connections, and to assist in testing.
- C. Acceptance Testing Preparation:
 - 1. Test insulation resistance for each panelboard bus, component, connecting supply, feeder, and control circuit.
 - 2. Test continuity of each circuit.
- D. Tests and Inspections:
 - 1. Perform each visual and mechanical inspection and electrical test for low-voltage air circuit breakers stated in NETA ATS, Paragraph 7.6 Circuit Breakers. Certify compliance with test parameters.
 - 2. Correct malfunctioning units on-site, where possible, and retest to demonstrate compliance; otherwise, replace with new units and retest.
 - 3. Perform the following infrared scan tests and inspections and prepare reports:
 - a. Initial Infrared Scanning: After Substantial Completion, but not more than 60 days after Final Acceptance, perform an infrared scan of each panelboard. Remove front panels so joints and connections are accessible to portable scanner.
 - b. Follow-up Infrared Scanning: Perform an additional follow-up infrared scan of each panelboard 11 months after date of Substantial Completion.
 - c. Instruments and Equipment:
 - 1) Use an infrared scanning device designed to measure temperature or to detect significant deviations from normal values. Provide calibration record for device.
- E. Panelboards will be considered defective if they do not pass tests and inspections.
- F. Prepare test and inspection reports, including a certified report that identifies panelboards included and that describes scanning results, with comparisons of the two scans. Include notation of deficiencies detected, remedial action taken, and observations after remedial action.

3.5 ADJUSTING

- A. Adjust moving parts and operable components to function smoothly, and lubricate as recommended by manufacturer.
- B. Set field-adjustable circuit-breaker trip ranges **as indicated**.
- C. Load Balancing: After Substantial Completion, but not more than 60 days after Final Acceptance, measure load balancing and make circuit changes. Prior to making circuit changes to achieve load balancing, inform Architect of effect on phase color coding.
 - 1. Measure loads during period of normal facility operations.
 - 2. Perform circuit changes to achieve load balancing outside normal facility operation schedule or at times directed by the Architect. Avoid disrupting services such as fax machines and on-line data processing, computing, transmitting, and receiving equipment.
 - 3. After changing circuits to achieve load balancing, recheck loads during normal facility operations. Record load readings before and after changing circuits to achieve load balancing.
 - 4. Tolerance: Maximum difference between phase loads, within a panelboard, shall not exceed 20 percent.

3.6 PROTECTION

- A. Temporary Heating: Prior to energizing panelboards, apply temporary heat to maintain temperature according to manufacturer's written instructions.

END OF SECTION 262416

SECTION 262726 - WIRING DEVICES

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:
 - 1. Straight-blade convenience
 - 2. Toggle switches.
 - 3. Wall plates.

1.3 DEFINITIONS

- A. BAS: Building automation system.
- B. EMI: Electromagnetic interference.
- C. GFCI: Ground-fault circuit interrupter.
- D. Pigtail: Short lead used to connect a device to a branch-circuit conductor.
- E. RFI: Radio-frequency interference.
- F. SPD: Surge protective device.
- G. UTP: Unshielded twisted pair.

1.4 ACTION SUBMITTALS

- A. Product Data: For each type of product.
- B. Shop Drawings: List of legends and description of materials and process used for premarking wall plates.
- C. Samples: One for each type of device and wall plate specified, in each color specified.

1.5 INFORMATIONAL SUBMITTALS

- A. Field quality-control reports.

1.6 CLOSEOUT SUBMITTALS

- A. Operation and Maintenance Data: For wiring devices to include in all manufacturers' packing-label warnings and instruction manuals that include labeling conditions.

PART 2 - PRODUCTS

2.1 GENERAL WIRING-DEVICE REQUIREMENTS

- A. Wiring Devices, Components, and Accessories: Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and application.
- B. Comply with NFPA 70.
- C. Devices that are manufactured for use with modular plug-in connectors may be substituted under the following conditions:
 - 1. Connectors shall comply with UL 2459 and shall be made with stranding building wire.
 - 2. Devices shall comply with the requirements in this Section.
- D. Devices for Owner-Furnished Equipment:
 - 1. Receptacles: Match plug configurations.
 - 2. Cord and Plug Sets: Match equipment requirements.
- E. Source Limitations: Obtain each type of wiring device and associated wall plate from single source from single manufacturer.

2.2 STRAIGHT-BLADE RECEPTACLES

- A. Duplex Convenience Receptacles: 125 V, 20 A; comply with NEMA WD 1, NEMA WD 6 Configuration 5-20R, UL 498, and FS W-C-596.

2.3 GFCI RECEPTACLES

- A. General Description:
 - 1. 125 V, 20 A, straight blade, feed-through type.
 - 2. Comply with NEMA WD 1, NEMA WD 6 Configuration 5-20R, UL 498, UL 943 Class A, and FS W-C-596.
 - 3. Include indicator light that shows when the GFCI has malfunctioned and no longer provides proper GFCI protection.
- B. Duplex GFCI Convenience Receptacles:

2.4 TOGGLE SWITCHES

- A. Comply with NEMA WD 1, UL 20, and FS W-S-896.
- B. Switches, 120/277 V, 20 A:
 - 1. Single Pole:

2.5 WALL PLATES

- A. Single and combination types shall match corresponding wiring devices.
 - 1. Plate-Securing Screws: Metal with head color to match plate finish.
 - 2. Material for Finished Spaces: **Steel with white baked enamel, suitable for field painting.**
 - 3. Material for Unfinished Spaces: **Galvanized steel.**
 - 4. Material for Damp Locations: **Cast aluminum** with spring-loaded lift cover, and listed and labeled for use in wet and damp locations.
- B. Wet-Location, Weatherproof Cover Plates: NEMA 250, complying with Type 3R, weather-resistant, **die-cast aluminum** with lockable cover.

2.6 FINISHES

- A. Device Color:
 - 1. Wiring Devices Connected to Normal Power System: **Almond** unless otherwise indicated or required by NFPA 70 or device listing.
 - 2. Wiring Devices Connected to Emergency Power System: **Red.**
 - 3. SPD Devices: **Blue.**
 - 4. Isolated-Ground Receptacles: **Orange.**
- B. Wall Plate Color: For plastic covers, match device color.

PART 3 - EXECUTION

3.1 INSTALLATION

- A. Comply with NECA 1, including mounting heights listed in that standard, unless otherwise indicated.
- B. Coordination with Other Trades:
 - 1. Protect installed devices and their boxes. Do not place wall finish materials over device boxes and do not cut holes for boxes with routers that are guided by riding against outside of boxes.
 - 2. Keep outlet boxes free of plaster, drywall joint compound, mortar, cement, concrete, dust, paint, and other material that may contaminate the raceway system, conductors, and cables.

3. Install device boxes in brick or block walls so that the cover plate does not cross a joint unless the joint is troweled flush with the face of the wall.
4. Install wiring devices after all wall preparation, including painting, is complete.

C. Conductors:

1. Do not strip insulation from conductors until right before they are spliced or terminated on devices.
2. Strip insulation evenly around the conductor using tools designed for the purpose. Avoid scoring or nicking of solid wire or cutting strands from stranded wire.
3. The length of free conductors at outlets for devices shall meet provisions of NFPA 70, Article 300, without pigtails.
4. Existing Conductors:
 - a. Cut back and pigtail, or replace all damaged conductors.
 - b. Straighten conductors that remain and remove corrosion and foreign matter.
 - c. Pigtailling existing conductors is permitted, provided the outlet box is large enough.

D. Device Installation:

1. Replace devices that have been in temporary use during construction and that were installed before building finishing operations were complete.
2. Keep each wiring device in its package or otherwise protected until it is time to connect conductors.
3. Do not remove surface protection, such as plastic film and smudge covers, until the last possible moment.
4. Connect devices to branch circuits using pigtails that are not less than 6 inches (152 mm) in length.
5. When there is a choice, use side wiring with binding-head screw terminals. Wrap solid conductor tightly clockwise, two-thirds to three-fourths of the way around terminal screw.
6. Use a torque screwdriver when a torque is recommended or required by manufacturer.
7. When conductors larger than No. 12 AWG are installed on 15- or 20-A circuits, splice No. 12 AWG pigtails for device connections.
8. Tighten unused terminal screws on the device.
9. When mounting into metal boxes, remove the fiber or plastic washers used to hold device-mounting screws in yokes, allowing metal-to-metal contact.

E. Receptacle Orientation:

1. Install ground pin of vertically mounted receptacles **down**, and on horizontally mounted receptacles to the **right**.

F. Device Plates: Do not use oversized or extra-deep plates. Repair wall finishes and remount outlet boxes when standard device plates do not fit flush or do not cover rough wall opening.

G. Arrangement of Devices: Unless otherwise indicated, mount flush, with long dimension vertical and with grounding terminal of receptacles on top. Group adjacent switches under single, multigang wall plates.

H. Adjust locations of floor service outlets and service poles to suit arrangement of partitions and furnishings.

3.2 GFCI RECEPTACLES

- A. Install non-feed-through-type GFCI receptacles where protection of downstream receptacles is not required.

3.3 IDENTIFICATION

- A. Comply with Section 260553 "Identification for Electrical Systems."
- B. Identify each receptacle with panelboard identification and circuit number. Use hot, stamped, or engraved machine printing with **black**-filled lettering on face of plate, and durable wire markers or tags inside outlet boxes.

3.4 FIELD QUALITY CONTROL

- A. Test Instruments: Use instruments that comply with UL 1436.
- B. Test Instrument for Convenience Receptacles: Digital wiring analyzer with digital readout or illuminated digital-display indicators of measurement.
- C. Perform the following tests and inspections.
 - 1. In healthcare facilities, prepare reports that comply with recommendations in NFPA 99.
 - 2. Test Instruments: Use instruments that comply with UL 1436.
 - 3. Test Instrument for Convenience Receptacles: Digital wiring analyzer with digital readout or illuminated digital-display indicators of measurement.
- D. Tests for Convenience Receptacles:
 - 1. Line Voltage: Acceptable range is 105 to 132 V.
 - 2. Percent Voltage Drop under 15-A Load: A value of 6 percent or higher is unacceptable.
 - 3. Ground Impedance: Values of up to 2 ohms are acceptable.
 - 4. GFCI Trip: Test for tripping values specified in UL 1436 and UL 943.
 - 5. Using the test plug, verify that the device and its outlet box are securely mounted.
 - 6. Tests shall be diagnostic, indicating damaged conductors, high resistance at the circuit breaker, poor connections, inadequate fault current path, defective devices, or similar problems. Correct circuit conditions, remove malfunctioning units and replace with new ones, and retest as specified above.
- E. Test straight-blade for the retention force of the grounding blade according to NFPA 99. Retention force shall be not less than 4 oz. (115 g).
- F. Wiring device will be considered defective if it does not pass tests and inspections.
- G. Prepare test and inspection reports.

END OF SECTION 262726

SECTION 262816 - ENCLOSED SWITCHES AND CIRCUIT BREAKERS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and other Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:
 - 1. Nonfusible switches.
 - 2. Molded-case circuit breakers (MCCBs).
 - 3. Enclosures.

1.3 DEFINITIONS

- A. NC: Normally closed.
- B. NO: Normally open.
- C. SPDT: Single pole, double throw.

1.4 ACTION SUBMITTALS

- A. Product Data: For each type of enclosed switch, circuit breaker, accessory, and component indicated. Include nameplate ratings, dimensioned elevations, sections, weights, and manufacturers' technical data on features, performance, electrical characteristics, ratings, accessories, and finishes.
 - 1. Enclosure types and details for types other than NEMA 250, Type 1.
 - 2. Current and voltage ratings.
 - 3. Short-circuit current ratings (interrupting and withstand, as appropriate).
 - 4. Include evidence of a nationally recognized testing laboratory (NRTL) listing for series rating of installed devices.
 - 5. Detail features, characteristics, ratings, and factory settings of individual overcurrent protective devices, accessories, and auxiliary components.
 - 6. Include time-current coordination curves (average melt) for each type and rating of overcurrent protective device; include selectable ranges for each type of overcurrent protective device. Provide in **PDF and** electronic format.
- B. Shop Drawings: For enclosed switches and circuit breakers.
 - 1. Include plans, elevations, sections, details, and attachments to other work.
 - 2. Include wiring diagrams for power, signal, and control wiring.

1.5 INFORMATIONAL SUBMITTALS

- A. Qualification Data: For qualified testing agency.
- B. Field quality-control reports.

1.6 CLOSEOUT SUBMITTALS

- A. Operation and Maintenance Data: For enclosed switches and circuit breakers to include in emergency, operation, and maintenance manuals.
 - 1. In addition to items specified in Section 017823 "Operation and Maintenance Data," include the following:
 - a. Manufacturer's written instructions for testing and adjusting enclosed switches and circuit breakers.
 - b. Time-current coordination curves (average melt) for each type and rating of overcurrent protective device; include selectable ranges for each type of overcurrent protective device. Provide in **PDF and** electronic format.

1.7 QUALITY ASSURANCE

- A. Testing Agency Qualifications: Accredited by NETA.
 - 1. Testing Agency's Field Supervisor: Currently certified by NETA to supervise on-site testing.

1.8 FIELD CONDITIONS

- A. Environmental Limitations: Rate equipment for continuous operation under the following conditions unless otherwise indicated:
 - 1. Ambient Temperature: Not less than minus 22 deg F (minus 30 deg C) and not exceeding 104 deg F (40 deg C).
 - 2. Altitude: Not exceeding 6600 feet (2010 m).

1.9 WARRANTY

- A. Manufacturer's Warranty: Manufacturer and Installer agree to repair or replace components that fail in materials or workmanship within specified warranty period.
 - 1. Warranty Period: **One** year from date of Substantial Completion.

PART 2 - PRODUCTS

2.1 PERFORMANCE REQUIREMENTS

2.2 GENERAL REQUIREMENTS

- A. Source Limitations: Obtain enclosed switches and circuit breakers, overcurrent protective devices, components, and accessories, within same product category, from single manufacturer.
- B. Product Selection for Restricted Space: Drawings indicate maximum dimensions for enclosed switches and circuit breakers, including clearances between enclosures, and adjacent surfaces and other items. Comply with indicated maximum dimensions.
- C. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, by an NRTL, and marked for intended location and application.
- D. Comply with NFPA 70.

2.3 NONFUSIBLE SWITCHES

- A. Type GD, General Duty shall not permitted.
- B. Type HD, Heavy Duty, Three Pole, Single Throw **600-V ac**, 1200 A and Smaller: UL 98 and NEMA KS 1, horsepower rated, lockable handle with capability to accept three padlocks, and interlocked with cover in closed position.
- C. Accessories:
 - 1. Equipment Ground Kit: Internally mounted and labeled for copper and aluminum ground conductors.
 - 2. Neutral Kit: Internally mounted; insulated, capable of being grounded and bonded; labeled for copper and aluminum neutral conductors.
 - 3. Isolated Ground Kit: Internally mounted; insulated, labeled for copper and aluminum neutral conductors.
 - 4. Auxiliary Contact Kit: **One Two** NO/NC (Form "C") auxiliary contact(s), arranged to activate before switch blades open. Contact rating **120-V ac**.
 - 5. Lugs: **Mechanical** type, suitable for number, size, and conductor material.
 - 6. Service-Rated Switches: Labeled for use as service equipment.

2.4 MOLDED-CASE CIRCUIT BREAKERS

- A. Circuit breakers shall be constructed using glass-reinforced insulating material. Current carrying components shall be completely isolated from the handle and the accessory mounting area.
- B. Circuit breakers shall have a toggle operating mechanism with common tripping of all poles, which provides quick-make, quick-break contact action. The circuit-breaker handle shall be over center, be trip free, and reside in a tripped position between on and off to provide local trip indication. Circuit-breaker escutcheon shall be clearly marked on and off in addition to providing

international I/O markings. Equip circuit breaker with a push-to-trip button, located on the face of the circuit breaker to mechanically operate the circuit-breaker tripping mechanism for maintenance and testing purposes.

- C. The maximum ampere rating and UL, IEC, or other certification standards with applicable voltage systems and corresponding interrupting ratings shall be clearly marked on face of circuit breaker. Circuit breakers shall be **100 percent rated**.
- D. Lugs shall be suitable for **194 deg F (90 deg C) rated wire, sized according to the 167 deg F (75 deg C) temperature rating in NFPA 70**.
- E. Standard: Comply with UL 489 with interrupting capacity to comply with available fault currents.
- F. Thermal-Magnetic Circuit Breakers: Inverse time-current thermal element for low-level overloads and instantaneous magnetic trip element for short circuits. Adjustable magnetic trip setting for circuit-breaker frame sizes 250 A and larger.
- G. Adjustable, Instantaneous-Trip Circuit Breakers: Magnetic trip element with front-mounted, field-adjustable trip setting.
- H. Ground-Fault Circuit-Interrupter (GFCI) Circuit Breakers: Single- and two-pole configurations with Class A ground-fault protection (6-mA trip).

2.5 ENCLOSURES

- A. Enclosed Switches and Circuit Breakers: UL 489, NEMA KS 1, NEMA 250, and UL 50, to comply with environmental conditions at installed location.
- B. Enclosure Finish: The enclosure shall be **gray baked enamel paint, electrodeposited on cleaned, phosphatized galvanized steel (NEMA 250 Types 3R, 12)**.
- C. Operating Mechanism: The circuit-breaker operating handle shall be **directly operable through the dead front trim of the enclosure (NEMA 250 Type 3R)**. The cover interlock mechanism shall have an externally operated override. The override shall not permanently disable the interlock mechanism, which shall return to the locked position once the override is released. The tool used to override the cover interlock mechanism shall not be required to enter the enclosure in order to override the interlock.

PART 3 - EXECUTION

3.1 EXAMINATION

- A. Examine elements and surfaces to receive enclosed switches and circuit breakers for compliance with installation tolerances and other conditions affecting performance of the Work.
- B. Proceed with installation only after unsatisfactory conditions have been corrected.
 - 1. Commencement of work shall indicate Installer's acceptance of the areas and conditions as satisfactory.

3.2 PREPARATION

- A. Interruption of Existing Electric Service: Do not interrupt electric service to facilities occupied by Owner or others unless permitted under the following conditions and then only after arranging to provide temporary electric service according to requirements indicated:
 - 1. Notify **Construction Manager** and **Owner** no fewer than five days in advance of proposed interruption of electric service.
 - 2. Indicate method of providing temporary electric service.
 - 3. Do not proceed with interruption of electric service without **Construction Manager's** and **Owner's** written permission.
 - 4. Comply with NFPA 70E.

3.3 ENCLOSURE ENVIRONMENTAL RATING APPLICATIONS

- A. Enclosed Switches and Circuit Breakers: Provide enclosures at installed locations with the following environmental ratings.
 - 1. Indoor, Dry and Clean Locations: NEMA 250, **Type 1**.
 - 2. Outdoor Locations: NEMA 250, **Type 3R**.
 - 3. Other Wet or Damp, Indoor Locations: NEMA 250, **Type 4**.
 - 4. Indoor Locations Subject to Dust, Falling Dirt, and Dripping Noncorrosive Liquids: NEMA 250, **Type 12**.

3.4 INSTALLATION

- A. Coordinate layout and installation of switches, circuit breakers, and components with equipment served and adjacent surfaces. Maintain required workspace clearances and required clearances for equipment access doors and panels.
- B. Install individual wall-mounted switches and circuit breakers with tops at uniform height unless otherwise indicated.
- C. Comply with mounting and anchoring requirements specified in Section 260548.16 "Seismic Controls for Electrical Systems."
- D. Temporary Lifting Provisions: Remove temporary lifting of eyes, channels, and brackets and temporary blocking of moving parts from enclosures and components.
- E. Install fuses in fusible devices.
- F. Comply with NFPA 70 and NECA 1.

3.5 IDENTIFICATION

- A. Comply with requirements in Section 260553 "Identification for Electrical Systems."
 - 1. Identify field-installed conductors, interconnecting wiring, and components; provide warning signs.

2. Label each enclosure with engraved metal or laminated-plastic nameplate.

3.6 FIELD QUALITY CONTROL

- A. Testing Agency: Owner will engage a qualified testing agency to perform tests and inspections.
- B. Testing Agency: Engage a qualified testing agency to perform tests and inspections.
- C. Manufacturer's Field Service: Engage a factory-authorized service representative to test and inspect components, assemblies, and equipment installations, including connections.
- D. Perform tests and inspections.
- E. Tests and Inspections for Switches:
 1. Visual and Mechanical Inspection:
 - a. Inspect physical and mechanical condition.
 - b. Inspect anchorage, alignment, grounding, and clearances.
 - c. Verify that the unit is clean.
 - d. Verify blade alignment, blade penetration, travel stops, and mechanical operation.
 - e. Verify that fuse sizes and types match the Specifications and Drawings.
 - f. Verify that each fuse has adequate mechanical support and contact integrity.
 - g. Inspect bolted electrical connections for high resistance using one of the two following methods:
 - 1) Use a low-resistance ohmmeter.
 - a) Compare bolted connection resistance values to values of similar connections. Investigate values that deviate from those of similar bolted connections by more than 50 percent of the lowest value.
 - 2) Verify tightness of accessible bolted electrical connections by calibrated torque-wrench method in accordance with manufacturer's published data or NETA ATS Table 100.12.
 - a) Bolt-torque levels shall be in accordance with manufacturer's published data. In the absence of manufacturer's published data, use NETA ATS Table 100.12.
 - h. Verify that operation and sequencing of interlocking systems is as described in the Specifications and shown on the Drawings.
 - i. Verify correct phase barrier installation.
 - j. Verify lubrication of moving current-carrying parts and moving and sliding surfaces.
 2. Electrical Tests:
 - a. Perform resistance measurements through bolted connections with a low-resistance ohmmeter. Compare bolted connection resistance values to values of similar connections. Investigate values that deviate from adjacent poles or similar switches by more than 50 percent of the lowest value.

- b. Measure contact resistance across each switchblade fuseholder. Drop values shall not exceed the high level of the manufacturer's published data. If manufacturer's published data are not available, investigate values that deviate from adjacent poles or similar switches by more than 50 percent of the lowest value.
- c. Perform insulation-resistance tests for one minute on each pole, phase-to-phase and phase-to-ground with switch closed, and across each open pole. Apply voltage in accordance with manufacturer's published data. In the absence of manufacturer's published data, use Table 100.1 from the NETA ATS. Investigate values of insulation resistance less than those published in Table 100.1 or as recommended in manufacturer's published data.
- d. Measure fuse resistance. Investigate fuse-resistance values that deviate from each other by more than 15 percent.
- e. Perform ground fault test according to NETA ATS 7.14 "Ground Fault Protection Systems, Low-Voltage."

F. Tests and Inspections for Molded Case Circuit Breakers:

1. Visual and Mechanical Inspection:

- a. Verify that equipment nameplate data are as described in the Specifications and shown on the Drawings.
- b. Inspect physical and mechanical condition.
- c. Inspect anchorage, alignment, grounding, and clearances.
- d. Verify that the unit is clean.
- e. Operate the circuit breaker to ensure smooth operation.
- f. Inspect bolted electrical connections for high resistance using one of the two following methods:
 - 1) Use a low-resistance ohmmeter.
 - a) Compare bolted connection resistance values to values of similar connections. Investigate values that deviate from those of similar bolted connections by more than 50 percent of the lowest value.
 - 2) Verify tightness of accessible bolted electrical connections by calibrated torque-wrench method in accordance with manufacturer's published data or NETA ATS Table 100.12.
 - a) Bolt-torque levels shall be in accordance with manufacturer's published data. In the absence of manufacturer's published data, use NETA ATS Table 100.12.
- g. Inspect operating mechanism, contacts, and chutes in unsealed units.
- h. Perform adjustments for final protective device settings in accordance with the coordination study.

2. Electrical Tests:

- a. Perform resistance measurements through bolted connections with a low-resistance ohmmeter. Compare bolted connection resistance values to values of similar

- connections. Investigate values that deviate from adjacent poles or similar switches by more than 50 percent of the lowest value.
- b. Perform insulation-resistance tests for one minute on each pole, phase-to-phase and phase-to-ground with circuit breaker closed, and across each open pole. Apply voltage in accordance with manufacturer's published data. In the absence of manufacturer's published data, use Table 100.1 from the NETA ATS. Investigate values of insulation resistance less than those published in Table 100.1 or as recommended in manufacturer's published data.
 - c. Perform a contact/pole resistance test. Drop values shall not exceed the high level of the manufacturer's published data. If manufacturer's published data are not available, investigate values that deviate from adjacent poles or similar switches by more than 50 percent of the lowest value.
 - d. Perform insulation resistance tests on all control wiring with respect to ground. Applied potential shall be 500-V dc for 300-V rated cable and 1000-V dc for 600-V rated cable. Test duration shall be one minute. For units with solid state components, follow manufacturer's recommendation. Insulation resistance values shall be no less than two megohms.
 - e. Determine the following by primary current injection:
 - 1) Long-time pickup and delay. Pickup values shall be as specified. Trip characteristics shall not exceed manufacturer's published time-current characteristic tolerance band, including adjustment factors.
 - 2) Short-time pickup and delay. Short-time pickup values shall be as specified. Trip characteristics shall not exceed manufacturer's published time-current characteristic tolerance band, including adjustment factors.
 - 3) Ground-fault pickup and time delay. Ground-fault pickup values shall be as specified. Trip characteristics shall not exceed manufacturer's published time-current characteristic tolerance band, including adjustment factors.
 - 4) Instantaneous pickup. Instantaneous pickup values shall be as specified and within manufacturer's published tolerances.
 - f. Test functionality of the trip unit by means of primary current injection. Pickup values and trip characteristics shall be as specified and within manufacturer's published tolerances.
 - g. Perform minimum pickup voltage tests on shunt trip and close coils in accordance with manufacturer's published data. Minimum pickup voltage of the shunt trip and close coils shall be as indicated by manufacturer.
 - h. Verify correct operation of auxiliary features such as trip and pickup indicators; zone interlocking; electrical close and trip operation; trip-free, anti-pump function; and trip unit battery condition. Reset all trip logs and indicators. Investigate units that do not function as designed.
 - i. Verify operation of charging mechanism. Investigate units that do not function as designed.
3. Correct malfunctioning units on-site, where possible, and retest to demonstrate compliance; otherwise, replace with new units and retest.
 4. Perform the following infrared scan tests and inspections and prepare reports:
 - a. Initial Infrared Scanning: After Substantial Completion, but not more than 60 days after Final Acceptance, perform an infrared scan of each enclosed switch and circuit

- breaker. Remove front panels so joints and connections are accessible to portable scanner.
 - b. Follow-up Infrared Scanning: Perform an additional follow-up infrared scan of each enclosed switch and circuit breaker 11 months after date of Substantial Completion.
 - c. Instruments and Equipment: Use an infrared scanning device designed to measure temperature or to detect significant deviations from normal values. Provide calibration record for device.
5. Test and adjust controls, remote monitoring, and safeties. Replace damaged and malfunctioning controls and equipment.
- G. Enclosed switches and circuit breakers will be considered defective if they do not pass tests and inspections.
- H. Prepare test and inspection reports.
- 1. Test procedures used.
 - 2. Include identification of each enclosed switch and circuit breaker tested and describe test results.
 - 3. List deficiencies detected, remedial action taken, and observations after remedial action.

3.7 ADJUSTING

- A. Adjust moving parts and operable components to function smoothly, and lubricate as recommended by manufacturer.

END OF SECTION 262816

SECTION 263100 - PHOTOVOLTAIC COLLECTORS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:
 - 1. PV system description.
 - 2. Manufactured PV units.
 - 3. PV module framing.
 - 4. PV array construction.
 - 5. Inverters.
 - 6. System overcurrent protection.
 - 7. Mounting structures.

1.3 DEFINITIONS

- A. CEC: California Energy Commission.
- B. ETFE: Ethylene tetrafluoroethylene.
- C. FEP: Fluorinated ethylene propylene.
- D. IP Code: Required ingress protection to comply with IEC 60529.
- E. MPPT: Maximum power point tracking.
- F. PTC: PVUSA Test Condition. Commonly regarded as a "real-world" measure of PV output. See below for definition of "PVUSA."
- G. PV: Photovoltaic.
- H. PVUSA: Photovoltaics for Utility Systems Applications.
- I. STC: Standard Test Conditions defined in IEC 61215.

1.4 ACTION SUBMITTALS

- A. Product Data: For each type of product.

1. Include construction details, material descriptions, dimensions of individual components and profiles, and finishes for PV panels.
2. Include rated capacities, operating characteristics, electrical characteristics, and furnished specialties and accessories.

B. Shop Drawings: For PV modules.

1. Include plans, elevations, sections, and mounting details.
2. Include details of equipment assemblies. Indicate dimensions, weights, loads, required clearances, method of field assembly, components, and location and size of each field connection.
3. Detail fabrication and assembly.
4. Include diagrams for power, signal, and control wiring.

1.5 INFORMATIONAL SUBMITTALS

- A. Field quality-control reports.
- B. Sample Warranty: For manufacturer's special materials and workmanship warranty and minimum power output warranty.

1.6 CLOSEOUT SUBMITTALS

- A. Operation and Maintenance Data: For PV modules to include in operation and maintenance manuals.

1.7 WARRANTY

- A. Manufacturer's Special Warranty: Manufacturer agrees to repair or replace components of PV modules that fail in materials or workmanship within specified warranty period.
 1. Manufacturer's materials and workmanship warranties include, but are not limited to, the following:
 - a. Faulty operation of PV modules.
 - b. Linear Power Performance Warranty
 2. Warranty Period:
 - a. Twenty Five years on materials and workmanship from date of Substantial Completion.
 - b. Thirty years on linear power performance
- B. Manufacturer's Special Minimum Power Output Warranty: Manufacturer agrees to repair or replace components of PV modules that fail to exhibit the minimum power output within specified warranty period. Special warranty, applying to modules only, applies to materials only, on a prorated basis, for period specified.
 1. Manufacturer's minimum power output warranties include, but are not limited to, the following warranty periods, from date of Substantial Completion:

- a. Specified minimum power output to **80** percent or more, for a period of 30 years.

PART 2 - PRODUCTS

2.1 PERFORMANCE REQUIREMENTS

- A. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and application.
- B. Hazardous Locations: FM Global approved for NFPA 70, Class 1, Division 2, Group C and Group D.

2.2 PV CAPACITIES AND CHARACTERISTICS

- A. Minimum Electrical Characteristics:
 1. Rated Open-Circuit Voltage: 39.6 V dc.
 2. Maximum System Voltage: 1500 V dc.
 3. Maximum Power at Voltage (V_{pm}): 33.4 V dc.
 4. Short-Circuit Temperature Coefficient: .045% /deg C>.
 5. Rated Short-Circuit Current (I_{sc}): 16 amps.
 6. Rated Operation Current (I_{mp}): 14.98 amps.
 7. Maximum Power at STC (P_{max}): 500 watts.

2.3 PV SYSTEMS DESCRIPTION

- A. Interactive PV System: Collectors connected in parallel to the TBPP main bus and BESS; and capable of providing power for Project and supplying power to a distributed network.
 1. A module array sized as noted on the project plans to generate a total nominal rated output as noted on the project plans.
 2. System Components:
 - a. PV modules.
 - b. Array frame.
 - c. BESS interactive inverter. BESS to be grid forming.
 - d. Overcurrent protection, disconnect, and rapid shutdown devices.
 - e. Mounting structure.
 - f. System kW/kWh meter.
 - g. DC combiner boxes.
- B. System shall be a Stand Alone PV system: Collectors connected to provide power to Project dc and ac loads through an energy storage system.

2.4 MANUFACTURED PV UNITS

- A. Cell Materials: N-Type TOPCon Technology

B. Module Construction:

1. Nominal Size: 44.6 inches (800 mm) wide by 77.2 inches (1600 mm) long.
2. Weight: 51.4 lb (19.4 kg).

C. Front Panel: Fully tempered glass.

D. Backing Material: Tempered glass.

E. Frame: Anodized aluminum

F. Bypass Diode Protection: Internal.

G. Junction Box:

1. Size: 1.56 by 3.96 by 0.52 inch (39.6 by 100.6 by 13.2 mm).
2. Fully potted, vandal resistant.
3. IP Code **IP68**.
4. Flammability Test: UL 1703.

H. Output Cabling:

1. Quick, multiconnect, polarized connectors.

I. Series Fuse Rating: 25 amp.

2.5 PV MODULE FRAMING

A. PV laminates mounted in anodized extruded-aluminum frames.

1. Entire assembly UL listed for electrical and fire safety, according to UL 1703, and complying with IEC 61215.
2. Frame strength exceeding requirements of certifying agencies in subparagraph above.
3. Finish: Anodized aluminum.
 - a. Alloy and temper recommended by framing manufacturer for strength, corrosion resistance, and application of required finish.
 - b. Color: As indicated by manufacturer's designations.

2.6 PV ARRAY CONSTRUCTION

A. Framing:

1. Material: **Extruded aluminum**.
2. Maximum System Weight: Less than 4 lb/sq. ft. (19.53 kg/sq. m).
3. Raceway Cover Plates **Aluminum**.

2.7 INVERTER

A. Inverter Type: String.

- B. Inverter size: AC output wattage as noted on project plans.
- C. Control Type: Maximum power point tracker control.
- D. Inverter Electrical Characteristics:
 - 1. Inverter shall have electrical ratings as listed for its size and are similar to those manufactured by SMA, SolarEdge, Chint (CPS), or equal.
- E. Operating Conditions:
 - 1. Operating Ambient Temperatures: Minus 4 to plus 122 deg F (20 to plus 50 deg C).
 - 2. Storage Temperature: Minus 40 to plus 122 deg F (minus 40 to plus 50 deg C).
 - 3. Relative Humidity: Zero to 95 percent, noncondensing.
- F. Enclosure:
 - 1. NEMA **Type 3R minimum**.
 - 2. Enclosure Material: **Steel**.
 - 3. Cooling Methods:
 - a. Passive cooling.
 - 4. Protective Functions:
 - a. AC over/undervoltage.
 - b. AC over/underfrequency.
 - c. Ground overcurrent.
 - d. Overtemperature.
 - e. AC and dc overcurrent.
 - f. DC overvoltage.
 - 5. Standard LCD, four lines, 20 characters, with user display and on/off toggle switch.
- G. Disconnects: Rated for system voltage and conductor.
- H. Regulatory Approvals:
 - 1. IEEE 1547.1.
 - 2. IEEE 1547.3.
 - 3. UL 1741.

2.8 SYSTEM OVERCURRENT PROTECTION

- A. Fuses: Per project plans requirements.
- B. Circuit Breakers: Per project plans requirements.

2.9 MOUNTING STRUCTURES

- A. Rack Mounts per project plans.

PART 3 - EXECUTION

3.1 EXAMINATION

- A. Examine substrate areas and conditions, with Installer present, for compliance with requirements for installation tolerances and other conditions affecting performance of the Work.
- B. Do not begin installation until mounting surfaces have been properly prepared.
- C. If preparation of mounting surfaces is the responsibility of another installer, notify Architect of unsatisfactory preparation before proceeding.
- D. Examine modules and array frame before installation. Reject modules and arrays that are wet, moisture damaged, or mold damaged.
- E. Examine roofs, supports, and supporting structures for suitable conditions where PV system will be installed.
- F. Proceed with installation only after unsatisfactory conditions have been corrected.

3.2 INSTALLATION

- A. Comply with NECA 1.
- B. Coordinate layout and installation of PV panels with [roof] [support] assembly and other construction.
- C. Support PV panel assemblies independent of supports for other elements such as roof and support assemblies, enclosures, vents, pipes, and conduits. Support assembly to prevent twisting from eccentric loading.
- D. Install PV [inverters,] [energy storage,] [charge controller,] [rapid shutdown,] [and] [system control] in locations indicated on Drawings.
- E. Install weatherseal fittings and flanges where PV panel assemblies penetrate exterior elements such as walls or roofs. Seal around openings to make weathertight. See Section 079200 "Joint Sealants" for materials and application.
- F. Seismic Restraints: Comply with requirements for seismic-restraint devices specified in Section 260548.16 "Seismic Controls for Electric Systems."
- G. Wiring Method: Install cables in raceways.
- H. Wiring within Enclosures: Bundle, lace, and train conductors to terminal points with no excess and without exceeding manufacturer's limitations on bending radii. Install lacing bars and distribution spools.

3.3 CONNECTIONS

- A. Coordinate PV panel cabling to equipment enclosures to ensure proper connections.
- B. Coordinate installation of utility-interactive meter with utility.
- C. Tighten electrical connectors and terminals according to manufacturer's published torque-tightening values. If manufacturer's torque values are not indicated, use those specified in UL 486A-486B.
- D. Make splices, terminations, and taps that are compatible with conductor material **and that possess equivalent or better mechanical strength and insulation ratings than unspliced conductors.**

END OF SECTION 263100

SECTION 263213.16 - GASEOUS EMERGENCY ENGINE GENERATORS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section includes packaged engine generators for emergency use with the following features:
 - 1. **Natural gas with LP backup** engine.
 - 2. Gaseous fuel system.
 - 3. Control and monitoring.
 - 4. Generator overcurrent and fault protection.
 - 5. Generator, exciter, and voltage regulator.
 - 6. Outdoor acoustic modified engine generator enclosure.
 - 7. Engine driven radiator.
 - 8. Vibration isolation devices.
 - 9. Finishes.
- B. Related Requirements:
 - 1. Section 263600 "Transfer Switches" for transfer switches including sensors and relays to initiate automatic-starting and -stopping signals for engine generators.

1.3 DEFINITIONS

- A. EPS: Emergency power supply.
- B. EPSS: Emergency power supply system.
- C. LP: Liquid petroleum.
- D. Operational Bandwidth: The total variation from the lowest to highest value of a parameter over the range of conditions indicated, expressed as a percentage of the nominal value of the parameter.

1.4 ACTION SUBMITTALS

- A. Product Data: For each type of product.
 - 1. Include rated capacities, operating characteristics, electrical characteristics, and furnished specialties and accessories.
 - 2. Include thermal damage curve for generator.
 - 3. Include time-current characteristic curves for generator protective device.

4. Include fuel consumption in cubic feet per hour (CFH) at 0.8 power factor at 0.5, 0.75, and 1.0 times generator capacity.
5. Include generator efficiency at 0.8 power factor at 0.5, 0.75, and 1.0 times generator capacity.
6. Include airflow requirements for cooling and combustion air in cubic feet per minute (CFM) at 0.8 power factor, with air-supply temperature of 95. Provide Drawings indicating requirements and limitations for location of air intake and exhausts.
7. Include generator characteristics, including, but not limited to, kilowatt rating, efficiency, reactances, and short-circuit current capability.

B. Shop Drawings:

1. Include plans and elevations for engine generator and other components specified.
2. Include details of equipment assemblies. Indicate dimensions, weights, loads, required clearances, method of field assembly, components, and location and size of each field connection.
3. Identify fluid drain ports and clearance requirements for proper fluid drain.
4. Design calculations for selecting vibration isolators and seismic restraints and for designing vibration isolation bases.
5. Vibration Isolation Base Details: Detail fabrication, including anchorages and attachments to structure and supported equipment. Include base weights.
6. Include diagrams for power, signal, and control wiring. Complete schematic, wiring, and interconnection diagrams showing terminal markings for EPS equipment and functional relationship between all electrical components.

1.5 INFORMATIONAL SUBMITTALS

A. Qualification Data: For **manufacturer.**

B. Seismic Qualification Data: Certificates, for engine generator, accessories, and components, from manufacturer.

1. Basis for Certification: Indicate whether withstand certification is based on actual test of assembled components or on calculation.
2. Dimensioned Outline Drawings of Equipment Unit: With engine and generator mounted on rails, identify center of gravity and total weight, **supplied enclosure, silencer**, and each piece of equipment not integral to the engine generator, and locate and describe mounting and anchorage provisions.
3. Detailed description of equipment anchorage devices on which the certification is based and their installation requirements.

C. Source Quality-Control Reports: Including, but not limited to, the following:

1. Certified summary of prototype-unit test report.
2. Certified Test Reports: For components and accessories that are equivalent, but not identical, to those tested on prototype unit.
3. Certified Summary of Performance Tests: Certify compliance with specified requirement to meet performance criteria for sensitive loads.
4. Report of factory test on units to be shipped for this Project, showing evidence of compliance with specified requirements.

5. Report of sound generation.
 6. Report of exhaust emissions showing compliance with applicable regulations.
 7. Certified Torsional Vibration Compatibility: Comply with NFPA 110.
- D. Field quality-control reports.
- E. Warranty: For special warranty.

1.6 CLOSEOUT SUBMITTALS

- A. Operation and Maintenance Data: For packaged engine generators to include in emergency, operation, and maintenance manuals.
1. In addition to items specified in Section 017823 "Operation and Maintenance Data," include the following:
 - a. List of tools and replacement items recommended to be stored at Project for ready access. Include part and drawing numbers, current unit prices, and source of supply.
 - b. Operating instructions laminated and mounted adjacent to generator location.
 - c. Training plan.

1.7 MAINTENANCE MATERIAL SUBMITTALS

- A. Furnish extra materials that match products installed and that are packaged with protective covering for storage and identified with labels describing contents.
1. Fuses: One for every 10 of each type and rating, but no fewer than one of each.
 2. Indicator Lamps: Two for every six of each type used, but no fewer than two of each.
 3. Filters: One set each of lubricating oil, fuel, and combustion-air filters.
 4. Tools: Each tool listed by part number in operations and maintenance manual.

1.8 QUALITY ASSURANCE

- A. Installer Qualifications: An authorized representative who is trained and approved by manufacturer.
- B. Testing Agency Qualifications: Accredited by NETA.
1. Testing Agency's Field Supervisor: Certified by NETA to supervise on-site testing.

1.9 WARRANTY

- A. Manufacturer's Warranty: Manufacturer agrees to repair or replace components of packaged engine generators and associated auxiliary components that fail in materials or workmanship within specified warranty period.
1. Warranty Period: 2 years from date of Substantial Completion.

PART 2 - PRODUCTS

2.1 MANUFACTURERS

- A. Source Limitations: Obtain packaged engine generators and auxiliary components from single source from single manufacturer.
- B. Acceptable manufacturers shall be those whose final, fully assembled packaged gaseous engine generator product meets or exceeds all performance requirements as specified herein for gaseous emergency engine generators.

2.2 PERFORMANCE REQUIREMENTS

- A. Seismic Performance: Engine generator housing, engine generator, batteries, battery racks, silencers, sound attenuating equipment, accessories, and components shall withstand the effects of earthquake motions determined according to **ASCE/SEI 7 level 4**.
 - 1. The term "withstand" means "the unit will remain in place without separation of any parts when subjected to the seismic forces specified[**and the unit will be fully operational after the seismic event**]."
 - 2. Shake-table testing shall comply with ICC-ES AC156. Testing shall be performed with all fluids at worst-case normal levels.
 - 3. Component Importance Factor: **1.0**.
- B. B11 Compliance: Comply with B11.19.
- C. NFPA Compliance:
 - 1. Comply with NFPA 37.
 - 2. Comply with NFPA 70.
 - 3. Comply with NFPA 99.
 - 4. Comply with NFPA 110 requirements for Level 1 EPSS.
- D. UL Compliance: Comply with UL 2200.
- E. Engine Exhaust Emissions: Comply with EPA Tier **2 for non-road SI engine** requirements and applicable state and local government requirements.
- F. Noise Emission: Comply with **applicable state and local government requirements** for maximum noise level due to sound emitted by engine generator, including engine, engine exhaust, engine cooling-air intake and discharge, and other components of installation. See silencer requirements in paragraph 2.4 in this specification. See enclosure requirements in paragraph 2.10 of this specification.
- G. Environmental Conditions: Engine generator system shall withstand the following environmental conditions without mechanical or electrical damage or degradation of performance capability:
 - 1. Ambient Temperature: **5 to 104 deg F**.
 - 2. Altitude: Sea level to **3000 feet**. Generator rated output shall be at the stated elevation.

- H. Unusual Service Conditions: Engine generator equipment and installation are required to operate under the following conditions:
 - 1. **High salt-dust content in the air due to sea-spray evaporation when installed within 50 miles of the coast.**

2.3 ENGINE GENERATOR ASSEMBLY DESCRIPTION

- A. Factory-assembled and -tested, water-cooled engine, with brushless generator and accessories.
- B. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and use.
- C. EPSS Class: Engine generator shall be classified as **Class 48** according to NFPA 110.
- D. Service Load: 500 kW/625 kVA.
- E. Power Factor: **0.8**, lagging.
- F. Frequency: 60 Hz.
- G. Voltage: 120/208V ac or 277/**480V** ac as required for the site
- H. Phase: Three-phase, four-wire **wye**.
- I. Induction Method: **Turbocharged**.
- J. Governor: Adjustable isochronous, with speed sensing.
- K. Mounting Frame: Structural-steel framework to maintain alignment of mounted components without depending on concrete foundation. Provide lifting attachments sized and spaced to prevent deflection of base during lifting and moving.
 - 1. **Rigging Diagram:** Inscribed on metal plate permanently attached to mounting frame to indicate location and lifting capacity of each lifting attachment and engine generator center of gravity.
- L. Capacities and Characteristics:
 - 1. **Power Output Ratings:** Nominal ratings as indicated at 0.8 power factor excluding power required for the continued and repeated operation of the unit and auxiliaries.
 - 2. **Nameplates:** For each major system component to identify manufacturer's name and address, and model and serial number of component.
- M. Engine Generator Performance:
 - 1. **Steady-State Voltage Operational Bandwidth:** 3 percent of rated output voltage, from no load to full load.

2. Transient Voltage Performance: Not more than 20 percent variation for 50 percent step-load increase or decrease. Voltage shall recover and remain within the steady-state operating band within three seconds.
3. Steady-State Frequency Operational Bandwidth: 0.5 percent of rated frequency, from no load to full load.
4. Steady-State Frequency Stability: When system is operating at any constant load within the rated load, there shall be no random speed variations outside the steady-state operational band and no hunting or surging of speed.
5. Transient Frequency Performance: Less than 5 percent variation for 50 percent step-load increase or decrease. Frequency shall recover and remain within the steady-state operating band within five seconds.
6. Output Waveform: At no load, harmonic content measured line to line or line to neutral shall not exceed 5 percent total and 3 percent for single harmonics. Telephone influence factor, determined according to NEMA MG 1, shall not exceed 50 percent.
7. Sustained Short-Circuit Current: For a three-phase, bolted short circuit at system output terminals, system shall supply a minimum of 250 percent of rated full-load current for not less than 10 seconds and then clear the fault automatically, without damage to generator system components.
8. Start Time: Comply with NFPA 110, **Type 10**, system requirements.

N. Engine Generator Performance for Sensitive Loads:

1. Oversizing generator compared with the rated power output of the engine is permissible to meet specified performance.
 - a. Nameplate Data for Oversized Generator: Show ratings required by the Contract Documents rather than ratings that would normally be applied to generator size installed.
2. Steady-State Voltage Operational Bandwidth: 1 percent of rated output voltage, from no load to full load.
3. Transient Voltage Performance: Not more than 10 percent variation for 50 percent step-load increase or decrease. Voltage shall recover and remain within the steady-state operating band within 0.5 second.
4. Steady-State Frequency Operational Bandwidth: Plus or minus 0.25 percent of rated frequency, from no load to full load.
5. Steady-State Frequency Stability: When system is operating at any constant load within the rated load, there shall be no random speed variations outside the steady-state operational band and no hunting or surging of speed.
6. Transient Frequency Performance: Less than 2-Hz variation for 50 percent step-load increase or decrease. Frequency shall recover and remain within the steady-state operating band within three seconds.
7. Output Waveform: At no load, harmonic content, measured line to neutral, shall not exceed 2 percent total with no slot ripple. Telephone influence factor, determined according to NEMA MG 1, shall not exceed 50 percent.
8. Sustained Short-Circuit Current: For a three-phase, bolted short circuit at system output terminals, system shall supply a minimum of 300 percent of rated full-load current for not less than 10 seconds and then clear the fault automatically, without damage to winding insulation or other generator system components.
9. Excitation System: Performance shall be unaffected by voltage distortion caused by nonlinear load.